



### BWNET NETOCOAX-01

network to coaxial converter for distances up to 2km

#### PRODUCT DESCRIPTION

##### ► Application:

Network over Coax solution Automatic bandwidth adaption pending on distance and cable

##### ► Technical specifications:

Type	Ethernet-Koax Media Wandler
Number of Ethernet ports	1x (female)
Ethernet standards	10Base-TX/100Base-TX
Ethernet connector	RJ-45
Ethernet speed	10 / 100 Mbit
Video data connector	1 x BNC, 1x 2 pin
Switch option	no
Distance RG59	Max: 2000m (see instructions)
Voltage	=12Vdc
Dimensions WxHxD (mm)	each 117 x 66 x 27.5
Weight	61 g
Rel. humidity (%)	Max. 95, non-condensing
Operating temperature (°C)	-30 bis +65
Specials	up to 2000m transmission

##### ► Note:

Lieferung exkl. Netzteile Empf. Netzteil: SNPS-12D2



BURG-GUARD GmbH  
 Wormgermühle, 58540 Meinerzhagen, Germany  
 Tel.: +49 2358 905 490, Fax: +49 2358 905 499  
 BURG-GUARD@burg.biz, www.burg-guard.com



### Weitere Bilder:



### ► Recommended Accessories

NWK-P0.55ES2	0,5m Patchcabel CAT5e, SF/UTP
NWK-P3.05ES2	3m Patchkabel CAT5e, SF/UTP
SNPS-12D2	SANTEC stabilized power supply 12 V DC, 1.5 A, plug