

DUAL FUEL PORTABLE GENERATOR 10,000 STARTING WATTS • 8,000 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY



1000

8500

8075

## **XP1000DX** DUAL FUEL PORTABLE GENERATOR

## **FEATURES**



## OUTLETS





## **SPECS**

| Watts (Gasoline)               | 10,000 (peak) • 8,000 (running) |
|--------------------------------|---------------------------------|
|                                |                                 |
| Watts (Propane)                | 9,500 (peak) • 7,600 (running)  |
| Engine                         | OHV 420cc                       |
| Amperage                       | 70.83A / 35.42A                 |
| Voltage                        | 120V / 240VAC                   |
| Fuel Type                      | Gasoline / Propane              |
| Runtime (Gasoline) at 50% Load | 10 hrs                          |
| Runtime (Propane) at 50% Load  | 9 hrs                           |