



XP10000E

PORTABLE GAS GENERATOR

10,000 STARTING WATTS • 8,000 RUNNING WATTS





XP10000E

PORTABLE GAS GENERATOR


FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- No-Flat Tires
- All-Copper Windings
- Fully-Loaded Power Panel
- Low Oil Shutoff
- Idle Control



DOUBLE THE 120V POWER

OUTLETS



X2
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V
30A Twist
Lock



X1
120/240V
50A Heavy
Duty Outlet

SPECS

Watts	10,000 (peak) • 8,000 (running)
Engine	OHV 439cc
Amperage	66.67A / 33.33A
Voltage	120V / 240VAC & 12VDC
Frequency	60 Hz
Fuel Type	Gasoline
Runtime at 50% Load	10.4 hrs
Start Type	Electric / Recoil