



# XP11500EH

## DUAL FUEL PORTABLE GENERATOR

11,500 STARTING WATTS • 9,000 RUNNING WATTS






# XP11500EH

DUAL FUEL PORTABLE GENERATOR

## FEATURES



## OUTLETS



**X2**  
120V 20A  
GFCI Outlet



**X1**  
120V 30A  
Twist Lock



**X1**  
120/240V  
30A Twist  
Lock



**X1**  
120/240V  
50A Heavy  
Duty Outlet

## SPECS

<b>Watts (Gasoline)</b>	11,500 (peak) • 9,000 (running)
<b>Watts (Propane)</b>	10,925 (peak) • 8,550 (running)
<b>Engine</b>	OHV 457cc
<b>Amperage</b>	75.00A / 37.50A
<b>Voltage</b>	120V / 240VAC
<b>Fuel Type</b>	Gasoline / Propane
<b>Runtime (Gasoline) at 50% Load</b>	8 hrs
<b>Runtime (Propane) at 50% Load</b>	6 hrs