



XP4400EH

DUAL FUEL PORTABLE GENERATOR
4,400 STARTING WATTS • 3,500 RUNNING WATTS






XP4400EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS



X2
120V 20A
GFCI Outlet



X1
120/240V
30A Twist
Lock



**DOUBLE THE
120V AMPERAGE**

SPECS

| | |
|---------------------------------------|--------------------------------|
| Watts (Gasoline) | 4,400 (peak) • 3,500 (running) |
| Watts (Propane) | 4,180 (peak) • 3,325 (running) |
| Engine | OHV 210cc |
| Amperage | 29.17A / 14.58A |
| Voltage | 120V / 240VAC & 12VDC |
| Fuel Type | Gasoline / Propane |
| Runtime (Gasoline) at 50% Load | 11.46 hrs |
| Runtime (Propane) at 50% Load | 9.81 hrs |