



# XP5500HX

DUAL FUEL PORTABLE GENERATOR

5,500 STARTING WATTS • 4,500 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY





# XP5500HX

DUAL FUEL PORTABLE GENERATOR


## FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- All-Copper Windings
- Digital Command Center
- Fully-Loaded Power Panel
- Exclusive MX2 Switch
- Low Oil Sensor



CO ALERT TECHNOLOGY

## OUTLETS



**X2**  
120V 20A  
GFCI Outlet



**X1**  
120/240V 30A  
Twist Lock



**X1**  
2.1A 1.0A  
USB Outlet



DOUBLE THE  
120V AMPERAGE

## SPECS

<b>Watts (Gasoline)</b>	5,500 (peak) • 4,500 (running)
<b>Watts (Propane)</b>	5,225 (peak) • 4,275 (running)
<b>Engine</b>	OHV 210cc
<b>Amperage</b>	37.50A / 18.75A
<b>Voltage</b>	120V / 240VAC & 5VDC
<b>Fuel Type</b>	Gasoline / Propane
<b>Runtime (Gasoline) at 50% Load</b>	8.82 hrs
<b>Runtime (Propane) at 50% Load</b>	7.63 hrs