

INDUCTIVE SENSOR ANALOG OUTPUT DW-Ax-509-M12

Long sensing range Exceptional price ✓ \checkmark HOUSING **OPERATING DISTANCE** MOUNTING √ Outstanding accuracy and perfmance ratio Quasitemperature stability \checkmark Current/voltage output M12 6 mm embeddable IP67 Resolution in µm range ✓ \checkmark Ũι C US LISTED ,,,,,,,, ASIC M12x1 M12x1 M12x1



DW-AD-509-M12







DW-AS-509-M12

DETECTION DATA

Sensing distance (S _d)	6 mm	IO-Link	×			
Repeat accuracy*	± 0.32 mm	MTTF (@40°C)	551 y			
Static resolution** (@0.67.S _d)	\leq 0.18 μm					
Dynamic resolution* (@ $0.67 \cdot S_d$)	\leq 0.9 μm					
Temperature drift on output signal***	≤± 10%					
Standard target	18 x 18 x 1 mm³, FE360					

INTERFACE

*Measured under 3σ confidence level (99.7%) at 0.67 Sd, constant temperature and constant voltage supply.

Static resolution is measured filtering the signal at 20 Hz. Dynamic resolution is measured filtering the signal at 1 kHz. *Over time a temperature drift of up to 10% can occur on the sensor, so regular calibration is recommended, depending on the application.

ELECTRICAL DATA		MECHANICAL DATA		
Supply voltage range (U _B)	1030 VDC	Mounting	Quasi-embeddable	
Residual ripple	\leq 20% U _B	Housing material	Chrome-plated brass	
Power consumption (no-load)	≤ 10 mA	Sensing face material	PBTP	
Max. load at voltage output	≤ 10 mA	Max tightening torque	10 Nm (6 Nm first 10 mm)	
Max. load at current output	1kΩ (Ub=10V) / 5kΩ (Ub=30V)	Ambient operating temperature	-25+70°C1	
Bandwidth	1000 Hz	Enclosure rating	IP 67	
Time delay before availability	20 ms	Weight (cable / connector)	see page 2	
Recovery time	20 ms	Shock and vibration	IEC 60947-5-7	
Warm-up time (temperature stability)	5 min			
Short-circuit protection	\checkmark			
Voltage reversal protection	\checkmark			
Cable length max.	≤ 300 m			
Note: all data measured according to IEC 60947	7-5-2 standard with $U_p=2030VDC$, $T_A=23^{\circ}C \pm 5^{\circ}C$	2.	¹ Maximum temperature according to UL: 70°C.	

prding to IEC 60947-5-2 standard with $U_p=20...30VDC$, $T_a=23^{\circ}C \pm 5^{\circ}C$

CONTRINEX AG Industrial Electronics

Route du Pâqui 3 - P.O. Box - CH 1720 Corminboeuf - Switzerland - Tel: +41 26 460 46 46 Fax: +41 26 460 46 40 - Internet: www.contrinex.com - E-mail: info@contrinex.com

CORRECTION FA	CTORS								
Steel FE 360	1	Copper	0.28	Aluminum	0.33	Brass	0.43	Stainless S. V2A 1 / 2 mm	0.8

Note: the operating distance of the sensor must be multiplied by the correction factor of the material. For example, the operating distance on Aluminum is $S_{n,AI} = S_n \times CF_{AI}$. In case of embeddable mounting, the distance is multiplied by the additional correction factor of the support, thus $S_{n,AI} = S_n \times CF_{AI} \times CF_{emb,AI}$.

RESPONSE DIAGRAM

7.00 b Α 6.00 С В 5.00 d Output Value [V] 4.00 Typical curves 3.00 2.00 1.00 0.00 a: 12 mm A : metal free zone 2.00 3.00 4.00 6.00 0.00 1.00 4.00 B : sensing face b: 14 mm Target Distance [mm] C : support c: 18 mm Steel FE 360 Copper Aluminium Brass Stainless d: steel 2 mm Steel V2A s = 0 0 V / -0.0 + 0.2 V s = 0 $1 \text{ mA} \pm 0.2 \text{ mA}$ Note: additional installation information can be found in the glossary of the $s = S_d/2$ $2.6 V \pm 0.2 V$ $s = S_d/2$ 3.1 mA ± 0.2 mA Contrinex General Catalog. Output Output $s = S_d$ $5.0 V \pm 0.2 V$ $5 \text{ mA} \pm 0.2 \text{ mA}$ $s = S_d$ voltage current 5...5.75 mA ± 0.2 5...6 V ± 0.2 V s > S_d s > S_d mA

WIRING DIAGRAM

INSTALLATION CONDITIONS



PIN ASSIGNMENT



AVAILABLE TYPES							
Part number	Part reference	Connection	Output on pin 2 / wh	Output on pin 4 / bk	Weight		
330-020-363	DW-AD-509-M12	PUR, 2 m, 4 wire	15 mA	05 V	87 g		
330-020-364	DW-AD-509-M12-120	PUR, 2 m, 4 wire	15 mA	05 V	80 g		
330-020-370	DW-AS-509-M12	M12 4-pin	15 mA	05 V	27 g		
330-020-371	DW-AS-509-M12-120	M12 4-pin	15 mA	05 V	23 g		

Note: part reference may include additional suffix to indicate a revision version or special version. Further information is available on request.

Product warranty is contingent upon professional use and proper installation of the product in applications for which the product was intended for, namely systems of automated manufacturing processes (factory automation). The warranty does not cover products that were modified, that have expired or that were subjected to physical, environmental, chemical or electrical stress. beyond their original design specifications. This product is not a safety component as defined by IEC-61508, ISO 13489 or other international safety standards. The manufacturer does not guarantee product performance in specific applications and does not warrant specifications in case of significant recurring temperature cycling. Terms of delivery and rights to change design reserved. All rights reserved.

CONTRINEX AG Industrial Electronics

Route du Pâqui 3-P.O. Box-CH 1720 Corminboeuf-Switzerland-Tel: +41264604646 Fax: +41 26 460 46 40 - Internet: www.contrinex.com - E-mail: info@contrinex.com

DW-Ax-509-M12_Rev 1_08.03.2024_PM-TK