1-Channel 10/100/1000M PoE Injector - 30W - IEEE 802.3af/at

This compact 30 watts PoE injector is a single port passive PoE injector. It can convert standard 100 ~ 240V/AC power into low voltage DC that runs over existing LAN cable to power up IEEE 802.3af/at compliant network accessories and IP security cameras. No external power supply is required providing a compact, cost effective and reliable power solution over existing Ethernet infrastructure.

Features: Up to 30W of power on 2-pairs / Supports 100/1000 Base-T applications / Power input LED indicators / Internal AC/DC converter / No need for external power supply / Easy plug-and-play installation / Multi-protection

	,				
Physical Characteristics					
No. of Channels	1				
Body Material	Plastic Enclosure				
Operating Temperature	-10°C to 40°C				
Storage Temperature	-10°C to 60°C				
Operating Humidity	Maximum 85% (no condensation)				
Storage Humidity	Maximum 90% (no condensation)				
Dimensions	145 x 60 x 40mm				
Connectors	Shielded RJ45, EIA 568A and 568B				
Indicators	PWR Indicator: AC Po	ower	PoE Ind	licator: Channel F	ower
Performance					
Pass Through Data Rates	100/1000 Mbps				
Max Power	30 Watts				
PoE Input Pin Assignment & Polarity	1/2 (-), 3/6(+)				
PoE Output Voltage	DC 50V, 0.6A				
User Port Power	15.4W & 30W				
AC Input Current/Voltage	0.5A / 100 to 240 VAC				
Frequency	50 to 60 Hz				
Over Current Protection	Yes				
Over Load Protection	Yes	<u>Approva</u>	<u>I</u>		
Over Voltage Protection	Yes	c(UL)us		Yes	
Anti-interference Protection	Yes	CE, FCC		Yes	
Environmental					
RoHS	Yes				
Packaging Information					
Package Quantity	1 - PoE Extender 1- 3 foot C13 to 5-15P Power Cable				
Package Weight	0.72 lbs [0.22kg]				

