



Premium Phantom Cables Dual Channel RCA Male to Male Audio Cable

RCA2-xx - Specifications

Description

This cable has RCA red and white male connectors on each end. It is typically used to connect left/right analog audio channels from a source to an output speaker.

- 22 gauge, heavy duty cable is used to capture all highs & lows for optimum audio performance
- Constructed of "Siamese" cable for easy installation of left and right audio
- Constructed of low-loss, stranded 22 gauge OFHC (Oxygen Free Copper) with a foam polyethylene insulation around center conductors
- 95% braided copper shield surrounds dielectric for maximum EMI/RFI noise rejection therefore maintaining the cleanest signal possible
- Multi-stranded copper center conductors allows for extra flexible cables
- High quality, 24K gold plated shielded connectors allows for optimum connectivity and maintains a clean signal integrity
- FT4 riser fire rated jacket for in-wall use
- Lead Free, "silver laced" solder is used in order to reduce loss and maximize conductivity

Physical Characteristics

Color	Red/White
Connector Plating	Gold
Cable Diameter	5.00mm x 10.0mm
Wire Gauge	22AWG
Jacket Material	PVC - Polyvinyl Chloride
Fire Rating	FT4 (Riser CMR)
Cable Shielding	95% Bare Copper Braid
Strain Relief	Metal Shell

Connectors

Connector A	RCA Red/White Male
Connector B	RCA Red/White Male

Environmental

RoHS	Yes
Reach	Yes
Conflict Materials	Yes

Package Information

Package Quantity	1
------------------	---

Cable Weights

	1.5ft	3ft	6ft	10ft	15ft
	0.45 lbs	0.5 lbs	0.80 lbs	1.00 lbs	1.35 lbs
	25ft	35ft	50ft	75ft	100ft
	2.00 lbs	2.65 lbs	3.65 lbs	5.30 lbs	7.00 lbs

