



Model

Artera Play+

General Description	CD Player, DAC, Pre-Amp
Key Technology & Features	DSD (up to DSD256 Compatible) Bluetooth aptX
Audio File Formats	ALAC, WAV, FLAC, AIFF, WMA, MP3, AAC, AAC- HE, AAC+, DSD64, DSD128, DSD256
D/A Converter	ESS ES9018 32bit DAC
USB Input	USB B (PC / MAC)
Digital Audio Inputs	2 × Optical TOSlink, 2 × RCA (DIG1, DIG2)
Digital Audio Outputs	1 × Optical TOSlink, 1 x RCA (DIG)
Analogue Inputs	2 × RCA (AUX1, AUX2)
Analogue Outputs	2 x RCA, 2 x Balanced XLR, 6.3mm Headphone Jack
Sample Rate (USB B)	44.1kHz, 48kHz, 88.2kHz, 96kHz, 176.4kHz, 192kHz, 384kHz
Sample Rate (USB A)	44.1kHz, 48kHz
Sample Rate (Digital Inputs / Outputs)	44.1 - 192kHz
Standby Power Consumption	<0.5W

Pre-Amplifier Section

Output Level (1kHz) Variable Output	0 - 4 Vrms (Pre Outputs) 0 – 8 Vrms (Balanced Outputs)
Frequency Response	20Hz-20kHz, 1kHz ($\pm$ 0.2dB)
Total Harmonic Distortion	<0.002% (20Hz-20kHz)
Signal to Noise Ration(S/N)	>103dB (1kHz) >110dB (A Weighted, 1kHz)
Channel Separation	>100dB (1kHz)
Dimensions (Unpacked) (H x W x D)	320 x 105 x 320mm
Net Weight	9.04kg