

JOB NAME:	
DATE:	
TYPE:	

## **DESCRIPTION**

Fully shielded, Full Cutoff wallpack. Full Cutoff optics with flat tempered glass lens. EZ mount knockouts for easy wiring. Lamp supplied.

## **SPECIFICATIONS**

#### **Cutoff Lens:**

Tempered glass.

#### Finish:

Chip and fade resistant polyester powder coating.

### Housing:

Die cast aluminum, 1/2" NPS tapped holes top, both sides and back for conduit or photocontrol. Hinged refractor frame. Continuous silicone rubber gasket.

#### Reflector:

Specular anodized aluminum, removable for installation. Symmetrical light pattern maximizes distance between fixtures.

### Refractor:

Prismatic optics designed to minimize glare and throw light down and out. Heat resistant borosilicate glass.

# **UL Listing:**

Suitable for wet locations. HID fixtures can be wired with 90° C supply wiring if supply wires are routed 3" away from ballast.

### Patents:

RAB sensor and fixture designs are protected under U.S. and International Intellectual Property laws.

## Photocell:

/PC2 = 277V

## **Quad Tap:**

Fixture works with 120, 208, 240, and 277 volts


### Color:

White

# Weight:


16.55

# **DIMENSIONS**



## **PHOTOMETRIC**

150w HPS @10' Mounting Height



Mounti Height	ng Multiplier
8'	1.6
10'	1.0
12'	.7
16'	.4
20'	.25

Input

Watts	Multi <sub>l</sub> HPS	olier MH	CFL
175		.9	
150PS		.9	
150	1.0	.8	
125PS		.7	
100	.6	.6	
70	.4	.4	
42			.2
84			.4

Lamp

Hours

24000

LAMP Initial

6400

S62

## ORDERING INFORMATION

**High Pressure Sodium** Total Lamp Lamp Starting Amps/ Operating Amps **Ballast** 120V 208V Lamp supplied with fixture Watts Type Base 70 ED17 Medium HX-HPF QT .8/.9 .5/.5

Button Photocontrol for 208 - 277 volt (/PC2)

240V

Note: Specifications may change without notice

**Factory Installed Options** 

Add suffix to Catalog Number

Tamperproof screws (/TP) Double fusing for 208 and 240 volt (/FF) Swivel Photocontrol (/PCS) Single fusing for 120 and 277 volt (/F) Button Photocontrol (/PC)

RAB Lighting, Inc. • 170 Ludlow Ave• Northvale, NJ 07647 • Tel: 888 RAB-1000 • Fax: 888 RAB-1232 • www.rabweb.com © 2010 RAB Lighting, Inc.