




H A Y L O U

Haylou-GT1
真无线蓝牙耳机
使用说明书

产品介绍



包装内容

蓝牙耳机，充电盒，耳帽x2对，说明书，充电线

佩戴耳机



通话时，将耳机麦克风朝向嘴部可使通话更清晰。

充电

开机使用前，请先撕掉左右耳机充电触点处的隔离膜，将充电盒及耳机充满电。



开机

耳机在充电盒内，从充电盒中拿出耳机自动开机。
耳机不在充电盒内且已关机，长按多功能键约1.5秒（白灯亮起）。



关机

放入充电盒中，耳机自动关机。
开机状态下，长按触控面板约4.5秒（红灯长亮2秒）。



拒听电话

来电时，长按触控面板约1秒拒听电话。



双耳机使用

自动连接：同时将两只耳机从充电盒取出，等待2-3秒耳机自动开机串联，待右耳机白灯慢闪时，打开设备蓝牙搜索“Haylou-GT1_R”并点击完成连接。如果连接失败，将耳机放回充电盒，重复上述操作。首次连接后，耳机开机可自动回连上一次配对设备（蓝牙需开启）。

注意：耳机出厂时已完成初始化，可直接取出进行相关操作。



手动连接：在耳机关机时，手动打开两只耳机，白灯快闪等待左右耳机串联，串联成功后右耳机白灯慢闪，打开设备蓝牙进行连接。

单耳机使用

自动连接：从充电盒取出一只耳机，自动开机后，指示灯由白灯快闪变成慢闪时，打开设备蓝牙搜索

“Haylou-GT1_R”（或者“Haylou-GT1_L”）并点击完成连接。

首次连接后，耳机开机可自动回连上一次配对设备（蓝牙需开启）。

注意：左耳机（L）自动回连时间相对较长。

手动连接：在耳机关机时，手动开启其中一只耳机，待耳机变成白灯慢闪时，打开设备蓝牙连接对应耳机。

耳机基本参数

通讯距离：10米（无障碍空旷环境）

电池容量：43mAh（单耳机）

充电时间：约1.5小时

通话时间：约3.5小时

待机时间：约150小时

输入参数：5V=100mA

电池类型：锂离子聚合物电池 无线连接：蓝牙5.0

充电盒基本参数

输入参数：5V=500mA

输出参数：5V=150mA

充电时间：约2小时

待机时间：约4个月

电池容量：310mAh

电池类型：锂离子聚合物电池

所有技术信息以实际性能为准

播放/暂停音乐

待机状态下，短按触控面板暂停/播放音乐。
注意：音乐播放器需处于后台运行状态。



开启语音助手

待机状态下，连续按三次触控面板开启语音助手。
注意：需设备支持语音功能且打开快速唤醒设置。



接听/挂断电话

来电时，短按触控面板二次接听来电；通话状态下，短按触控面板二次挂断电话。



音乐上一曲/下一曲

轻按左耳机触控面板两次，上一曲；
轻按右耳机触控面板两次，下一曲。

接听第二个来电并切换通话

当手机来电时，短按触控面板2次接听电话进行通话；
手机通话中有新来电时，短按多功能键保持上一个通话，进行第二个来电的通话；短按两下多功能键可切换两个通话。

耳机和手机听筒切换

通话状态下，长按触控面板约1秒可切换至耳机/手机听筒。

耳机重置

如果耳机无法正常连接使用，请参照以下方式重置耳机：将耳机拿出充电盒，在关机状态下，分别长按两只耳机多功能键约15秒，在第二次红白灯交替闪三次后松开并放回充电盒，将设备上面的连接记录删除后重新连接。（包括清除两只耳机配对串联和与设备配对的记录）

售后服务与支持

保修期：

签收次日起12个月

免费服务：

在产品保修期内，凡属产品本身质量引起的故障，请用户凭此说明书和购物凭证与经销商取得联系以享受免费维修

以下情况恕不免费维修：

1. 产品维修标签已破坏
2. 自行拆卸造成损坏的
3. 因进水或跌落而造成的的故障及人为机械损坏的
4. 因不可抗力造成故障或损坏的

注意

1. 若产品超过两个星期未使用，建议使用前先对产品进行充电；
2. 必须选择正规厂家生产的经过国家CCC认证的充电器；
3. 长时间连续使用耳机有损听力健康，请合理控制使用时间及音量；
4. 使用耳机会降低对外界声音的感知力，请不要在可能威胁到安全的环境中使用耳机。

产品中有害物质的名称及含量

部件名称	有害物质					
	铅 (Pb)	汞 (Hg)	镉 (Cd)	六价铬 (Cr(VI))	多溴联苯 (PBB)	多溴二苯醚 (PBDE)
耳机主体	X	○	○	○	○	○
电 池	○	○	○	○	○	○
耳 套	○	○	○	○	○	○
配 件	○	○	○	○	○	○
充 电 线	X	○	○	○	○	○

本表格依据SJ/T 11364的规定编制

○：表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572规定的限量要求以下。

X：表示该有害物质至少在该部件的某一均质材料中的含量超出GB/T 26572规定的限量要求。

使用期限

如本手册所述，在正常使用条件下，本产品的环保使用期限为5年。在此期间，产品不会泄露任何危险物质，本产品可以回收，必须按照当地法规处理。

若有售后服务需求,请联系Haylou客服

制造商：东莞市猎声电子科技有限公司

制造商地址：东莞市南城街道周溪社区隆溪路5号高盛科技园二期之高盛科技大厦第13层1303、1305、1306单元

生产厂：东莞峥嵘电子有限公司

生产厂地址：广东省东莞市洪梅镇疏港大道4号

网 址：www.haylou.com 执行标准：Q/LS 1-2018

客服电话：4008-555-083

Haylou蓝牙耳机三包凭证

Haylou蓝牙耳机售后服务承诺：严格依据《中华人民共和国消费者权益保护法》、《中华人民共和国产品质量法》实行售后三包服务，服务内容如下：

在三包有效期内，您可依照本规定享受修理、更换、退货的权利，修理、更换、退货应当凭说明书和购物凭证办理。

1. 自您签收次日起7日内，本产品出现《蓝牙耳机性能故障表》所列性能故障的情况，经由Haylou售后服务中心检测确定，可享受退货、换货或修理服务；
2. 自您签收次日起15日内，本产品出现《蓝牙耳机性能故障表》所列性能故障的情况，经由Haylou售后服务中心检测确定，可享受换货或修理服务；
3. 自您签收次日起12个月内，本产品出现《蓝牙耳机性能故障表》所列性能故障的情况，经由Haylou售后服务中心检测确定，可享受修理服务。

蓝牙耳机性能故障表

名称	性能故障
蓝牙耳机	1.蓝牙耳机听不到声音 2.通话过程中,对方听不到声音 3.无法为蓝牙耳机充电



CMIT ID: 2019DP2517



RoHS

提示

1. 使用产品前请仔细阅读本使用说明书并请妥善保管；
2. 首次使用时，请先将本产品充满电；
3. 如果产品长期(超过2个星期)不用，请对其充电；
4. 必须选择正规厂家生产且经过国家CCC认证的充电器；
5. 若手机无法搜索蓝牙耳机，请确认蓝牙耳机是否处于“配对模式”，若长时间未进行配对或连接，蓝牙耳机配对功能机配对功能将关闭，请重新开启蓝牙耳机至“配对模式”；若手机程序出错，请重启手机；若蓝牙耳机程序出错，请重启蓝牙耳机或者恢复出厂设置

警告

- 请勿以任何理由拆除或维修改装耳机，否则可能会导致起火，电子击穿甚至彻底损坏本产品；
- 请勿将产品置于温度过低或过高(0°C以下或45°C以上的环境下)；
- 请避免靠近儿童或动物的眼睛使用产品指示灯；
- 请勿在雷暴天气下使用该产品，雷暴可导致本产品工作不正常，并增加触电的危险；
- 请勿用油及其他挥发性液体擦拭本产品；

注意：长时间使用耳机可能会造成听力损害，请合理安排使用时间。

本耳机不支持输出超过2A的充电座给耳机充电，否则会损害耳机本体。




H A Y L O U

Haylou-GT1
TWS BT Earphones
User Manual

Overview

Charging Case



What's in the Box

BT earphones, charging case, EarTips × 2 pairs, user manual, charging cable

Earphones




Large



Small

Medium EarTips have been assembled in advance. However, you may try large or small ones, if the medium ones do not fit you well.



Please keep Mic
outside when calling



When calling, adjust Mic towards mouth to gain clear calling

Power-on

Take out earphones from the case to power on them.
Or touch both panels for 1.5s to power on earphones
(LED glows solid white) when they are not in the case.



Power-off

Put earphones into the case to power off them.
Or touch both panels for 4.5s to power off earphones
(LED glows solid red for 2s).



Ignore Call

Touch the panel for 1s to ignore incoming call.




Stereo Mode

Auto pairing: take out both EarBuds from the case and they will auto pair with each other in 2 or 3s. Earphones will be connectable to cellphone when LED on right EarBud blinks white slowly. On cellphone, search for "Haylou-GT1_R" and tap to connect.

If earphones fail to be connected to cellphone, please put EarBuds back to the case and repeat the above steps. Earphones will auto reconnect to the last device in connectivity records, if any.

Note: earphones have been setted to factory when shipping out.



Manual pairing: manually power on two EarBuds and they will auto pair with each other when LED blinks white promptly. Then LED on the right EarBud will blink white slowly and now you can tap it on cellphone to connect.

Mono Mode

Auto pairing: take out one EarBud from the case to power on it. Its LED will soon blink slowly then search for Haylou-GT1 R/L on cellphone and tap to connect. EarBud will auto reconnect to last device in connectivity records, if any.

Note: it may take more times for the left EarBud to reconnect.

Manual pairing: manually power on one EarBud. Its LED will soon blink white slowly then search for it on cellphone and tap to connect.

How to Charge

Prior to using, please peel off sticker on the pogo pins and top up the earphones



Play/pause

When standby, touch the panel to pause/play music.
Note: media player should run in background.



Voice Assistant

When standby, triple touch the panel to activate voice assistant.

Note: device needs to support voice assistant and fast awakening be turned on.



Answer/End Call

Double touch the panel to answer incoming call and double touch the panel again to end it.



Skip Track Forward/backward

Touch the panel on right earbud twice to skip track forward

Touch the panel on left earbud twice to skip track backward

Three-way Calling & Switch

Touch the panel twice to answer incoming call from phone. if another call is coming in sync , touch the panel to put the first call on hold while activating the second one. Double touch the panel to switch between active call and held call.

Switch Audio Output

When calling, touch the panel for 1s to switch audio output between earphones and cellphone.

Factory Setting

If earphones do not function well, please refer the following steps to reset factory: take EarBuds out from the case. Power off the earphones then touch both panels for about 15s (LED will blink red and white three times twice). After that, put them back to the case. Delete connectivity record on cellphone before processing another pairing (All connectivity records relating to the EarBuds will all be removed)

Basic Parameters

Operation range: 10m(with no obstacle)

Battery capacity: 43mAh(single EarBud)

Charging time: approx. 1.5hr

Calling time: approx. 3.5hr

Standby time: approx. 150hr

Input parameter: 5V= 100mA

Battery type: li-ion

Wireless connection: BT 5.0

Charging case

Input parameter:5V= 500mA

Output parameter:5V= 150mA

Charging time: approx. 2hr

Standby time: approx. 4 months

Battery capacity: 310mAh

Battery type: li-ion

Caveats

1. Never disassemble or modify your headset for any reasons to avoid any damages and danger.
2. Do not store the headset in extreme temperatures (under 0°C or over 45°C).
3. Avoid using the indicator close to the eyes of children or animals.
4. Do not use this headset during a thunderstorm to avoid irregular function and increased risk of electric shock.
5. Do not use harsh chemicals or strong detergents to clean the headset.
6. Keep the headset dry.

Warranty Card

Warranty Period

12 months after the next day receiving this item.

Free exchange service will not be accessed under following circumstances:

1. Damages caused unauthorized disassembly.
2. Defects or physical damages caused by leaking or dropping off.
3. Damages by act of God. Supposing your item is within any damages or defects except the above circumstances, please return to us or your distributor for free repairing.

Tips

1. Before using the headset, please read the manual carefully and keep it for future references.
2. The headset need to be fully charged prior to first-time use.
3. If the headset is left unused for over two weeks, please recharge it periodically.
4. Please use the chargers made by qualified manufacturer.
5. If the headset cannot be found by your phone, please check whether it is in pairing mode; if left unconnected for a long while, the headset will exit pairing mode, please re-enter the mode; if a procedure error of your phone occurs, reboot it; if a procedure error of the headset occurs, reboot or reset it.

Address: Suite 1303, 1305 and 1306, 13/F, Project Phrase 2 of Gaosheng Tech Tower, Gaosheng Tech Park, No.5 Longxi Road, Zhouxi Community, Nancheng District, Dongguan City, Guangdong, China.

Manufacturer: Dongguan Liesheng Electronic Co., Ltd.

Web: www.haylou.com

Perform standard: Q/LS 1-2018

Made In China

Hazardous substances and their contents in the item



Part Name	Hazardous Substances					
	(Pb)	(Hg)	(Cd)	(Cr(VI))	(PBB)	(PBDE)
Main body	X	○	○	○	○	○
Battery	○	○	○	○	○	○
Ear tips	○	○	○	○	○	○
Accessories	○	○	○	○	○	○
Charging cable	X	○	○	○	○	○

This form is made by SJ/T 11364 regulation.

○ : means that hazardous substance content in the homogeneous materials of this part is within the limits of GB/T 26572 regulation.

X : means that hazardous substance content in, at least, one certain homogeneous material of this part is beyond the limits of GB/T 26572 regulation.

Notes: Please arrange using time properly as your hearing may be damaged by using the device for a long time.



CMIT ID: 2019DP2517



RoHS