



# **Wall Plate**

## D-WP4AW

### Features:

### 1. Multi-Channel Signal Distribution

4 TV Outputs + 1 FM/AM Radio Output - Ideal for multi-room TV and audio distribution.

Dual-Input Source Selection - Switch between Terrestrial Antenna and Cable TV via ON/OFF toggle.

Satellite Signal Pass-Through - Direct F-type connector for uninterrupted satellite signal transmission.

extenders, and other network devices.

2. Dual-Power Supply System

12V/50mA DC Output - Powers TV antennas without

3. Wide Frequency Compatibility

Dedicated 12V/1.5A Wi-Fi Power Port - Supports routers,

Terrestrial/Cable TV: 47-862MHz

AM/FM Radio: 0.5-108MHz

external adapters.

www.dylux.com



| Specification    |   |
|------------------|---|
| Model            | D-WP4AW                                     |
| Output Ports     | 4×TV (TV1-TV4), 1×FM/AM                     |
| Input Ports      | 1×Terrestrial Antenna, 1×Cable TV           |
| Power Supply     | TV Antenna: DC 12V/50mA, Wi-Fi: DC 12V/1.5A |
| Signal Switching | Manual ON/OFF (Terrestrial/Cable TV)        |
| Connector Type   | F-Type (Coaxial)                            |
| Mounting         | Wall-Mounted (Fixed Installation)           |

### **Applications**

- 1. Home & Commercial Multi-TV Systems
- 3. Smart Home & Network Hubs

- 2. RV/Marine/Outdoor AV Setups
- 4. Satellite & Cable TV Integration

### **Wiring Diagram**

