



EF1000iS

1 kVA Inverter Generator

Introducing the EF1000iS Inverter Generator, which delivers maximum output with minimum effort. This generator is small, lightweight, and powerful generator is also portable with many excellent features. It can power camping fridge, fan, TV, computer and electric hand drill.

Equipped with a newly designed muffler and air filter, as well as Yamaha's advanced Noise Block™ sound reduction system, this generator is incredibly quiet. You can have a conversation without raising your voice, and you might not even notice it's running.



SPECIFICATIONS

Model	EF1000iS
Maximum Output	1000 Watts
Rated Output	900 Watts
Operating Hours (1/4 Load)	12 hr
Fuel Tank Capacity	2.5 L
Dry Weight	12.7 kg
Size (LxWxH)	450x240x380 mm
Noise Level (1/4 Load / 7m)	47 dBA
Noise Level (Full Load / 7m)	57 dBA
Starting System	Recoil
Independent Fuel Tap	Yes

FEATURES AT A GLANCE

- **USFS-Approved Spark Arrestor** eliminates errant sparks.
- **OHV Engine With Cast Iron Cylinder Liner** for longer life, powerful performance and excellent heat dissipation.
- **Smart Throttle™** varies engine speed based on load to improve fuel economy and reduce noise.
- **Petrol Petcock** helps prevent carburettor contamination during storage.
- **Oil Warning System** prevents engine damage.
- **Auto-Decompression System** reduces compression for effortless starting.
- **Inverter System with PWM (Pulse Width Modulation)** to safely run products with built-in microcomputers or microcomputer-controlled equipment/tools.
- **Electrical Overload Breaker** prevents generator damage in case of overload.
- **Controls Located On One Panel** for easy access.
- **Easily Detachable Side Panels** for easier serviceability.
- **Multi-Polar Alternator** for the generation of high quality, high frequency 3-phase AC current. This means a much lighter and a more compact unit when compared to conventional 2-pole rotor type alternators.