

1800 428 699

Portable Petrol Generator EP8000HSR

8 kVA Honda Powered Petrol Generator

This 8 kVA Generator is the perfect size for almost everything, with 2 x 15 amp outlets, and Honda Australia Approved GX390 engine, this generator will run your power tools, compressor, Welder and much more.

Specifications

| Power Rating: | 8 kVA |
|--------------------------------------|--------------------|
| Alternator Rating: | 9.5 kVA |
| Engine Model: | Honda GX390 |
| Phase: | 1 phase |
| Starting System: | Recoil |
| Fuel Tank Capacity: | 6.1 L |
| Noise Level @ 7m: | 74 dBA |
| Outlets: | 2 x 15 Amp |
| Volts: | 230 V |
| Approx. Fuel Consumption @ 80% Load: | 2.58 L/Hr |
| Operation Hours @ 80% Load: | 2.36 hrs |
| Fuel Type: | Petrol |
| Dimensions: | 810 x 545 x 545 mm |
| Weight: | 80 kg |



*Specifications are subject to change without notice







www.gentechgenerators.com.au