

EP8000HSRE Portable Petrol Generator with E-Start

## 8 kVA Honda Powered Petrol Generator with E-Start

8 kVA portable generator powered by Honda petrol engine with electric start. It is the perfect size for almost everything, with 2 x 15 amp outlets, and Honda Australia Approved GX390 engine, this generator will run your power tools, compressor, Welder and much more.

### Specifications

|                                      |                    |
|--------------------------------------|--------------------|
| Power Rating:                        | 8 kVA              |
| Alternator Rating:                   | 9.5 kVA            |
| Engine Model:                        | Honda GX390        |
| Phase:                               | 1 phase            |
| Starting System:                     | Recoil/Electric    |
| Fuel Tank Capacity:                  | 6.1 L              |
| Noise Level @ 7m:                    | 74 dBA             |
| Outlets:                             | 2 x 15 Amp         |
| Volts:                               | 230 V              |
| Approx. Fuel Consumption @ 80% Load: | 2.58 L/Hr          |
| Operation Hours @ 80% Load:          | 2.36 hrs           |
| Fuel Type:                           | Petrol             |
| Dimensions:                          | 810 x 545 x 545 mm |
| Weight:                              | 85 kg              |



*\*Specifications are subject to change without notice*

POWERED by  
**HONDA**

