

LeonLite

LED EMERGENCY LIGHT



Wet Location Outdoor Emergency Light **2 PACK**

- 4W** Wattage
- 120V/277V** Voltage
- 400lm** Luminous flux
- IP65** Waterproof rating
- 32°F-104°F** Working temp
- About 24hours** Charging time
- 120°** Beam angle
- Nickel cadmium battery** Battery type
- ABS** Material
- 3.6V 2000mAh** Battery capacity



- LED source eliminates the trouble of replacing the bulbs and provides bright light
- Suitable for harsh environments thanks to the EVA insulation making the light fit the wall well and increasing airtightness
- Built-in 3.6V 2000mAh battery, minimum 90mins working hours after fully charged for 24 hours
- The detachable cover prevents the light from damage caused by dust, water and insects
- UL-listed for quality assurance and safe operation, backed by a 2-year warranty

Caution

PLEASE turn off the power at the fuse box or circuit breaker before installing. ONLY use on 120V/277V circuits. Wet location rated. DO NOT use where direct water exposure occurs as this can lead to electric shocks. DO NOT use this fixture near any source of heat. PLEASE keep this product out of the reach of children under 3 years old.

Warranty

LeonLite warrants that this product is free from defects in materials and workmanship for a period of 2 years from the day of purchase. This warranty does not apply if the product has been damaged through misuse, abuse, accident, modifications, alterations, neglect or mishandling.



LeonLite

LED EMERGENCY LIGHT



Wet Location Outdoor Emergency Light **2 PACK**

- 4W** Wattage
- 120V/277V** Voltage
- 400lm** Luminous flux
- IP65** Waterproof rating
- 32°F-104°F** Working temp
- About 24hours** Charging time
- 120°** Beam angle
- Nickel cadmium battery** Battery type
- ABS** Material
- 3.6V 2000mAh** Battery capacity



- LED source eliminates the trouble of replacing the bulbs and provides bright light
- Suitable for harsh environments thanks to the EVA insulation making the light fit the wall well and increasing airtightness
- Built-in 3.6V 2000mAh battery, minimum 90mins working hours after fully charged for 24 hours
- The detachable cover prevents the light from damage caused by dust, water and insects
- UL-listed for quality assurance and safe operation, backed by a 2-year warranty

Caution

PLEASE turn off the power at the fuse box or circuit breaker before installing. ONLY use on 120V/277V circuits. Wet location rated. DO NOT use where direct water exposure occurs as this can lead to electric shocks. DO NOT use this fixture near any source of heat. PLEASE keep this product out of the reach of children under 3 years old.

Warranty

LeonLite warrants that this product is free from defects in materials and workmanship for a period of 2 years from the day of purchase. This warranty does not apply if the product has been damaged through misuse, abuse, accident, modifications, alterations, neglect or mishandling.

