HARDWARESOURCE HINGE SKU 268601

Blum 155 Degree Special Application Hinge for Face Frame Overlay Cabinets HOW TO CHOOSE THE CORRECT MOUNTING PLATE

step 1	Mea rou	APPOXIMATE CONVERSION CHART		
STEP 2	Me a dire	3mm	1/8"	
~	with	4mm 5mm	5/32"	
	1 Close the cabinet door.			3/16"
	-		5.5mm	7/32"
	2	Apply a piece of tape vertically to the hinged side of the cabinet so the edge of the tape is flush		1/4"
		against the hinged edge of the door. This marks how much the door overlaps the frame.	7mm	9/32"
	3	Open the door until you see the edge of the tape between the door and cabinet. Measure from the	8mm	5/16"
	Ŭ	inside edge of the tape to the opening of the cabinet door. This is your overlay dimension.	9mm	11/32"
STEP	One	9.5mm	3/8"	
3	whi	10mm	13/32"	
U	the ran	11mm	7/16"	
		12mm	15/32"	
	Exa ing	13mm	1/2"	
	pla	13.5mm	17/32"	
			14mm	9/16"

		BORE DISTANCE					
		Змм	4мм	5мм	6мм	7мм	8мм
OVERLAY RANGE	9мм то 13мм	3mm Plate (SKU 652305)					
	10мм то 14мм		3mm Plate (SKU 652305)				
	11мм то 15мм			3mm Plate (SKU 652305)			
	12мм то 16мм	Omm Plate (SKU 652304)			3mm Plate (SKU 652305)		
	13мм то 17мм		Omm Plate (SKU 652304)			3mm Plate (SKU 652305)	
	14мм то 18мм			Omm Plate (SKU 652304)			3mm Plate (SKU 652305)
	15мм то 19мм				Omm Plate (SKU 652304)		
	16мм то 20мм					Omm Plate (SKU 652304)	
	17мм то 21мм						Omm Plate (SKU 652304)

CONVERSION CHART					
3mm	1/8"				
4mm	5/32"				
5mm	3/16"				
5.5mm	7/32"				
6mm	1/4"				
7mm	9/32"				
8mm	5/16"				
9mm	11/32"				
9.5mm	3/8"				
10mm	13/32"				
11mm	7/16"				
12mm	15/32"				
13mm	1/2"				
13.5mm	17/32"				
14mm	9/16"				
15mm	19/32"				
16mm	5/8"				
17mm	11/16"				
18mm	23/32"				
19mm	3/4"				
20mm	25/32"				
20.5mm	7/8"				
21mm	27/32"				
22mm	7/8"				
23mm	29/32"				
24mm	15/16"				
25.4mm	1"				
26mm	1–1/32"				
27mm	1–1/16"				
28mm	1–3/32"				
29mm	1–1/18"				
30mm	1–3/16"				
31mm	1–7/32"				
32mm	1–1/4"				
33mm	1–5/16"				
34mm	1–11/32"				
35mm	1–3/8"				

