Salice 155 Degree Hinge for Frameless Overlay Cabinets **HOW TO CHOOSE THE CORRECT MOUNTING PLATE**

sтер 1	Me lar		APPOXIMATE CONVERSION CHART		
sтер 2	Measure your door overlay. The overlay is how much the door overlaps the cabinet. The following directions will tell you how to measure it. For further clarification, there is a link on			3mm 4mm	1/8" 5/32"
	the product page with more detailed instructions.				3/16"
	1	Close the cabinet door.		5.5mm	7/32"
	±				1/4"
	2 3	Apply a piece of tape vertically to the hinged side of the cabinet so the edge of the tape		7mm	9/32"
		is flush against the hinged edge of the door. This marks how much the door overlaps the frame.			5/16"
				9mm	11/32"
		Open the door until you see the edge of the tape between the door and cabinet. Measure			3/8"
		from the inside edge of the tape to the opening of the cabinet door. This is your overlay dimension.		10mm	13/32"
					7/16"
STEP	Once you know the bore distance and overlay of your door, you can use the chart below to			12mm	15/32"
3	determine which mounting plate you need.				1/2"
					17/32"

		BORE DISTANCE					
		Змм	4мм	5мм	6мм	7мм	8мм
	1.5мм то 7.5мм	12mm Plate (SKU 268714)					
	2.5мм то 8.5мм		12mm Plate (SKU 268714)				
OVERLAY RANGE	3.5мм то 9.5мм			12mm Plate (SKU 268714)			
	4.5мм то 10.5мм				12mm Plate (SKU 268714)		
	5.5мм то 11.5мм					12mm Plate (SKU 268714)	
	6.5мм то 12.5мм						12mm Plate (SKU 268714)
	11.5мм то 17.5мм	2mm Plate (SKU 268713)					
	12.5мм то 18.5мм		2mm Plate (SKU 268713)				
	13.5мм то 19.5мм			2mm Plate (SKU 268713)			
	14.5мм то 20.5мм				2mm Plate (SKU 268713)		
	15.5мм то 21.5мм					2mm Plate (SKU 268713)	
	16.5мм то 22.5мм						2mm Plate (SKU 268713)

CONVERSION CHART					
3mm	1/8"				
4mm	5/32"				
5mm	3/16"				
5.5mm	7/32"				
6mm	1/4"				
7mm	9/32"				
8mm	5/16"				
9mm	11/32"				
9.5mm	3/8"				
10mm	13/32"				
11mm	7/16"				
12mm	15/32"				
13mm	1/2"				
13.5mm	17/32"				
14mm	9/16"				
15mm	19/32"				
16mm	5/8"				
17mm	11/16"				
18mm	23/32"				
19mm	3/4"				
20mm	25/32"				
20.5mm	7/8"				
21mm	27/32"				
22mm	7/8"				
23mm	29/32"				
24mm	15/16"				
25.4mm	1"				
26mm	1–1/32"				
27mm	1–1/16"				
28mm	1–3/32"				
29mm	1–1/18"				
30mm	1–3/16"				
31mm	1–7/32"				
32mm	1–1/4"				
33mm	1–5/16"				
34mm	1–11/32"				
35mm	1–3/8"				

Hardware **Source**