



| M077A-4140 | | | | Controller: | | KBS |
|------------|----------------|---------|-------------|--------------|----------|---------|
| Volt (V) | Current (Amps) | Pin (W) | Speed (rpm) | Torque (N·m) | Pout (W) | Eff (%) |
| 48.01 | 0.460 | 22.11 | 1999 | 0.040 | 8.384 | 37.92 |
| 48.01 | 0.561 | 26.92 | 1981 | 0.069 | 14.22 | 52.82 |
| 48.02 | 0.737 | 35.37 | 1954 | 0.108 | 22.09 | 62.45 |
| 47.99 | 0.965 | 46.30 | 1917 | 0.164 | 32.83 | 70.91 |
| 47.97 | 1.271 | 60.97 | 1869 | 0.195 | 38.15 | 62.57 |
| 47.99 | 1.659 | 79.60 | 1813 | 0.295 | 56.07 | 70.44 |
| 47.99 | 2.103 | 100.9 | 1753 | 0.412 | 75.55 | 74.88 |
| 47.93 | 2.535 | 121.5 | 1696 | 0.534 | 94.92 | 78.12 |
| 47.95 | 3.044 | 146.0 | 1636 | 0.673 | 115.3 | 78.97 |
| 47.93 | 3.609 | 173.0 | 1571 | 0.833 | 137.0 | 79.19 |
| 47.88 | 4.241 | 203.1 | 1506 | 1.013 | 159.7 | 78.63 |
| 47.88 | 4.970 | 238.0 | 1435 | 1.220 | 183.4 | 77.06 |
| 47.85 | 5.773 | 276.2 | 1364 | 1.445 | 206.3 | 74.69 |