



	20		6	Controller:		KLS
Voltage (v)	Current (A)	PowerIn (w)	Speed (rpm)	NM	PowerOut (w)	Eff (%)
48.19	4.269	205.7	1921	0.156	31.45	15.29
48.17	4.109	197.9	1923	0.185	37.33	18.86
48.14	4.582	220.5	1922	0.253	50.85	23.06
48.15	5.070	244.1	1921	0.373	75.02	30.73
48.14	5.839	281.1	1919	0.561	112.7	40.09
48.11	6.987	336.2	1918	0.828	166.3	49.46
48.08	8.296	398.9	1916	1.172	235.1	58.94
48.00	10.04	482.0	1914	1.547	310.0	64.32
47.97	11.61	557.1	1912	1.937	387.7	69.59
47.77	18.16	867.3	1905	2.689	536.3	61.84
47.72	19.33	922.2	1894	3.630	720.0	78.07
47.67	21.50	1025	1883	4.284	844.4	82.38
47.57	24.45	1163	1875	4.953	972.4	83.61
47.47	27.91	1325	1878	5.645	1110	83.77
47.38	30.72	1456	1877	6.376	1253	86.06
47.30	33.91	1604	1868	7.137	1396	87.03
47.22	36.71	1734	1858	7.805	1518	87.54
47.13	39.91	1881	1851	8.566	1661	88.30
47.05	43.20	2033	1848	9.325	1805	88.79
46.97	46.30	2175	1841	10.04	1937	89.06
46.88	49.81	2335	1838	10.80	2078	88.99
46.79	53.30	2494	1830	11.55	2213	88.73
46.72	56.25	2628	1818	12.33	2348	89.35
46.63	59.65	2782	1813	13.14	2495	89.68
46.53	63.54	2956	1814	14.01	2662	90.05
46.46	67.19	3121	1811	14.83	2813	90.13
46.38	70.45	3267	1799	15.59	2937	89.90
46.29	74.01	3426	1787	16.50	3087	90.11