



	27		6	Controler:		KLS
Voltage (v)	Current (A)	PowerIn (w)	Speed (rpm)	NM	PowerOut (w)	Eff (%)
48.97	2.149	105.2	1453	0.168	25.52	24.26
48.95	2.396	117.3	1454	0.268	40.80	34.78
48.95	3.343	163.6	1453	0.548	83.32	50.93
48.90	4.543	222.1	1452	0.952	144.8	65.20
48.86	6.136	299.8	1451	1.431	217.4	72.52
48.81	7.820	381.7	1447	2.041	309.2	81.01
48.75	10.15	494.8	1444	2.715	410.6	82.98
48.69	12.34	601.0	1435	3.477	522.6	86.96
48.60	15.22	739.7	1429	4.330	647.8	87.58
48.53	18.02	874.3	1425	5.231	780.4	89.26
48.43	21.32	1033	1425	6.195	924.5	89.50
48.34	24.42	1181	1421	7.165	1066	90.26
48.27	27.55	1330	1409	8.192	1209	90.90
48.17	30.61	1474	1402	9.253	1359	92.20
48.05	34.42	1654	1402	10.34	1517	91.72
47.94	38.24	1833	1396	11.47	1676	91.43
47.84	41.90	2005	1388	12.64	1837	91.62
47.77	45.31	2164	1379	13.77	1989	91.91
47.66	49.47	2358	1376	15.00	2161	91.65
47.58	53.38	2540	1369	16.19	2320	91.34
47.50	56.85	2700	1361	17.33	2470	91.48
47.37	60.96	2888	1355	18.46	2620	90.72
47.27	65.34	3089	1344	19.91	2803	90.74
47.17	69.80	3292	1333	21.25	2966	90.10
47.09	74.12	3491	1331	22.55	3141	89.97