



	34		6	Controller:		KLS
Voltage (v)	Current (A)	PowerIn (w)	Speed (rpm)	NM	PowerOut (w)	Eff (%)
72.58	1.957	142.1	1658	0.165	28.57	20.11
72.56	2.509	182.1	1658	0.237	41.23	22.64
72.56	2.779	201.6	1661	0.524	91.10	45.19
72.52	4.053	293.9	1661	0.957	166.4	56.62
72.48	5.397	391.1	1657	1.424	247.1	63.18
72.45	6.822	494.3	1649	2.025	349.7	70.75
72.43	8.130	588.8	1641	2.704	464.6	78.91
72.36	10.09	730.2	1636	3.402	582.8	79.81
72.32	12.02	869.1	1634	4.315	738.0	84.92
72.26	14.42	1042	1629	5.269	898.6	86.24
72.19	17.18	1240	1616	6.366	1077	86.85
72.13	19.78	1427	1620	7.416	1258	88.16
72.06	22.28	1606	1613	8.503	1436	89.41
72.01	24.76	1783	1596	9.703	1622	90.97
71.93	27.73	1995	1592	10.86	1810	90.73
71.84	30.86	2217	1593	12.07	2012	90.75
71.77	33.75	2422	1581	13.26	2194	90.59
71.71	36.13	2591	1572	14.40	2370	91.47
71.63	39.11	2801	1567	15.58	2557	91.29
71.51	41.52	2969	1558	16.71	2727	91.85
71.44	44.37	3170	1550	17.79	2887	91.07
71.44	46.90	3351	1548	18.84	3054	91.14
			1500	24.3		