



44		6		Controler:		KLS
Voltage (v)	Current (A)	PowerIn (w)	Speed (rpm)	NM	PowerOut (w)	Eff (%)
144.2	1.050	151.3	1501	0.088	13.83	9.14
143.6	1.263	181.4	1500	0.154	24.20	13.34
143.9	1.495	215.3	1500	0.426	66.83	31.04
143.6	2.014	289.2	1501	0.834	131.1	45.33
143.6	2.705	388.4	1501	1.367	214.9	55.33
143.9	3.352	482.4	1500	2.055	322.8	66.92
143.8	4.172	599.7	1500	2.838	445.8	74.34
143.6	5.142	738.6	1499	3.684	578.4	78.31
143.7	5.933	852.8	1500	4.569	717.5	84.13
143.6	7.101	1020	1500	5.509	865.5	84.85
143.6	8.181	1175	1500	6.456	1014	86.30
143.6	9.349	1343	1500	7.517	1181	87.94
143.7	10.41	1496	1500	8.575	1347	90.04
143.5	11.68	1676	1500	9.598	1507	89.92
143.4	12.79	1835	1499	10.62	1667	90.84
143.6	13.91	1998	1500	11.59	1821	91.14
143.4	15.08	2163	1499	12.58	1975	91.31
143.5	15.99	2294	1500	13.56	2129	92.81
143.4	17.12	2455	1500	14.46	2271	92.51
143.5	18.23	2615	1500	15.36	2412	92.24
143.4	19.15	2746	1499	16.21	2545	92.68
143.3	20.09	2878	1500	16.96	2665	92.60
143.3	20.94	2999	1500	17.68	2778	92.63
143.3	21.62	3097	1501	18.34	2882	93.06