

NOARK®

Noark

2188 Pomona Blvd.

Pomona, CA 91768

Phone: 626.330.7007

Fax: 626.330.8035

Email: nasales@noark-electric.com

Website: www.noarkelectric.com

Catalog Number Ex9C115E22T, Ex9C Series 480 Volt (V) Alternating Current (AC)/Direct Current (DC) Coil Voltage and 115 Ampere (A) Current Standard IEC Contactor

NOARK® Electric Ex9C contactors are intended for various applications including heavy industrial loads. Nine frame sizes allow optimization of electrical parameters and mechanical dimensions. A range of overload relays are available in a variety of frame sizes to fit respective contactors of given rated current. 5-Year limited warranty.

Ex9R 185 Ampere Accessories



[Specifications](#) | [Dimensions](#) | [Certifications](#) | [Features](#) | [Downloads](#)

Specifications

Brands	NOARK®	
Number of Poles	3	
Auxiliary Contacts	2 Normally Open (NO) + 2 Normally Closed (NC) 3 Normally Open (NO)	
Alternating Current (AC)/Direct Current (DC) Coil Voltage	480 V	
Current	115 A	

Dimensions

Dimension F	4.75 in	120 mm
Dimension G	6.81 in	173 mm

Dimension G1	6.30 in 160 mm	
Dimension H	8.07 in	205 mm
Dimension H1	6.85 in 205 mm	
Dimension H2	4.25 in	108 mm
Dimension I	3.94 in 100 mm	
Mounting Hole Diameter (J)	0.28 in	7 mm
Note for Diameter J	It has only two mounting holes as broken circles and the other types have four mounting holes.	
Dimension K	5.12 in	130 mm

Certifications

Certifications

- UL 508 Listed File Number E3553866 / UL 60947-1 and 60947-4-1
- Certified for Canada according to CSA C22.2 No. 14
- IEC/EN 60947-4-1
- CE approved
- CCC Certified
- RoHS Compliant

Features

Features

- Nine frame sizes with rated current up to 1000 A at 690 V AC-3
- Coil control voltages available in AC and DC with ranges from 24-600 V.
- Wide range electronic coil available for 9-500 A contactors features built-in surge suppression.
- DIN rail 35 mm and panel mountable

Downloads

Data Sheet

[Ex9CS Series 6 to 12 Ampere \(A\) Current Miniature IEC Contactors \(Ex9C Data Sheet 2020 NOARK\)](#)

Instruction Booklet

[Ex9C Series 115 to 225 Ampere \(A\) Current Standard IEC Contactors \(Ex9C115 1000 IB NOARK\)](#)

Video MP4	Ex9C Series Standard IEC Contactors Video
White Paper	Non-Reversing Safety Contactors (Safety Contactor White Paper NOARK)
DWG - 2D CAD Drawing	Ex9C Series 24 Volt (V) Alternating Current (AC)/Direct Current (DC) Coil Voltage and 115 Ampere (A) Current Standard IEC Contactor (CAD Drawing)
DXF - 2D CAD Drawing	Ex9C Series 24 Volt (V) Alternating Current (AC)/Direct Current (DC) Coil Voltage and 115 Ampere (A) Current Standard IEC Contactor (Drawing -DXF)
PDF - 2D CAD Drawings	Ex9C Series 24 Volt (V) Alternating Current (AC)/Direct Current (DC) Coil Voltage and 115 Ampere (A) Current Standard IEC Contactor (Downloadable)