Feature List Specifications

FutureCall



Issue Date: 10-Jan-23

	Descriptions	FC-0914
	1 Line/2 Line (PSTN)	1
	Multiple Handset System	Yes
	Handsets-expands to #	4
		(cordless handset)
	Handset Rename	Yes (max 10 char)
	Tianuset iteriaine	Tes (max to onal)
	Handsets barge in outside call	No
	Intercom HS to HS	Yes (support up to 1pair only)
	Intercom HS to base	N/A
	Intercom to HS to all	No
	Transfer calls- HS to HS	Yes
	Calls announced number only	No
	Slow playback	No
	Any Key Answer on HS	No
	Auto Off (by putting on cradle)	Yes
_	Tone/Pulse Dialing	Yes; Default Tone
General	Temporary Touch Tone	Yes for Plus dialing only
ane.	Pre-Dialing	Yes
ŏ	Display Dial	Yes
	Speed Dial	M1 , M2 Keys 1,2,3 Long Push
	Emergency Dial	911 One Press Dial
	Speakerphone dialing from handset	Yes
	Handset Speakerphone	Yes
	Redial	Last 10 numbers
	Add Redlial to Block list	Yes Yes
	Flash (Swap) Reject call	No Yes
	Hold Feature	No
	Mute Feature	Yes (EEPROM Option)
	Headset Jack	No
	Dial Pad on base	No
	Belt Clip	No
	Wall Mountable	No
	Hearing Aid Compatible (EU)	Yes
	Support Voice Mail (VMWI)	Yes
	Clear Voice Mail indicator	Yes
	Set Date and Time	Yes
	Text language support	EN, FR, SP, PT, DE, NL, IT
	Support Line Power mode Handset	No
		HTN, positive, transflective
	HS LCD Type HS Size (VA)	40 (w) x 27 (h) mm
	TIO SIZE (VA)	n n
	HS Display	
Display	number of characters and number of lines	12 characters (2 lines icon + 1 line Dot Matrix + 1 line 7-segement)
di	Enlarge dialing digite	No
S	Enlarge dialing digits Touch screen	No No

Feature List Specifications

Issue Date: 10-Jan-23

	Descriptions	FC-0914
	Call Timer	Yes
	Real Time Clock	Yes
	Contrast Adjustment	Yes
	Base Unit	
	BS LCD Type	N/A
	BS Size (VA)	N/A
	BS No. of Dots	N/A
	Touch screen	N/A
	Call Timer	N/A
	Real Time Clock	N/A
	Brightness Adjustment	N/A
	Handset	
	Earpiece Volume control (L1/intercom, L2)	Yes (5 Steps)
	Speakerphone Volume control	Yes (5 Steps)
	Equalizer	No
es	Audio Assist for Earpiece only	Yes, (+10dB on top of normal level)
Audio Features	Ringer- Selectable	5 mono, 5 polyphonic tones
L 0	Ringer-polyphonic precanned	No
jgr	Ringer- Recordable	No
₹	Ringer-Vibrating	No
	Ringer Volume Control	5 steps
	Voice Announce (Talking CID)	No
	Talking CID (number only)	No
	Talking Digit	No
	Talking Phonebook	No
Z Đ	Battery type	2.4V 300mAH AAAx2
Battery (Handset)		
3att an	Standby time	100 hrs
" ∃	Talk Time	10 hrs
5	Name/Number List	50 (saved in Base)
Caller ID Feature	Memory (Phonebook) Match (I.e. Mom and Dad)	Yes
Ë	Memory (Phonebook) Ringtone Match	Yes
₽	Voice Announce (Talking CID) Type II CID (include USA requirement)	No Yes
<u>e</u>	Save CID into phone book	Yes
Sal	Save CID into block list	Yes
	Caller ID delete # of phonebook entry x # digits x # characters	Yes 100 (saved in Base) x 16 digits x 12 characters
Phonebook	Phonebook Edit	Yes
leb	Phonebook Delete	Yes
пог	Add Phonebook to VIP Talking Phonebook	Yes No
효	1-char/3-char search	1- char search
	Handset	
	Low Battery Audible Warning	Yes
)e)	Out of range alert	Off-hook: Yes
(tor	Keytone control	On-hook: No
ts	Message Alert tone	Yes (ON/ OFF) N/A
Alerts (tone)	Base Unit	
•	Low Battery Audible Warning	N/A
	Keytone control	No N/A
	Message Alert tone	N/A
	Handset Charging	Yes
S	Keypad backlit	res Amber
ato D	LCD backlit	Amber
ED Indicators		
ln c	Visual Ringer indicator	RED
Q:	Audio Assist	No
	Base Unit	

FC-0914 Feature List Specifications

Issue Date: 10-Jan-23

	Descriptions	FC-0914
	Charging	Yes
	Line in use or Answer Key for PSTN line(s)	Yes
Others	Support Reverse Charging	No
	ECO mode	NO
0	Alarm	Yes
	Telephone Plug	NO
	AC adaptor	Black, 1.5m, 2-round pins
	Line cord	Black, 1.5m, RJ11-RJ11

Feature List Specifications


Issue Date: 10-Jan-23

Descriptions	FC-0914
Descriptions	FC-0914

Product & Key Functions



Handset / Base Station Keys



1	OK / Menu key
2	Back / Intercom key
3 & 4	Navigation key
5	Hang-up / Exit key
6	# key - Press to insert #;
	In idle mode: Press and hold to access the call list.
7	0 key - During a call: Press and hold to insert a flash (R).
8	* key - Press to insert *; In idle mode: press and hold to access
	the redial lis
9	M1, M2 key - In idle mode/during a call: Press to dial pre- recorded number stored in direct mem.
10	911 Quick Dial Key
	One press to dial out 911 emergency number.
11	Talk key/Loudspeaker
12	Paging key - To locate handset/to start registration
	procedure.