

Falcon Electronics Single Ear Stereo Headset Part #: FBTHS01

1. Notice Before Using


Thank you for purchasing the Falcon Electronics Bluetooth® Headset (FBTHS01). Please read this User's Manual completely before you use the Headset. The FBTHS01 has been developed using Bluetooth[®] wireless technology and is capable of connecting with Bluetooth[®] devices designed with Audio Gateway. PDAs, Desktops and Notebook computers can be connected and paired with the Headset using a USB Bluetooth® Dongle or built-in Bluetooth capability (if applicable). Before using the Headset please verify your Bluetooth[®] device (Phone, PDA) complies with Bluetooth[®] V1.1/V1.2/V2.0/V2.1 and supports the Bluetooth[®] Headset or Hands-free profile.

2. Package Contents List

Please inspect this package and refer to the package contents list below to verify all items were included in this package:

A. FBTHS01 headset	1
B. AC Wall Charger	1
C. DC Car Charger	1
D. USB Charging Cable	1
E. User's Manual	
F. Extra Ear Pad and Mic Cover	2

3. FBTHS01 Bluetooth[®] Headset Overview



4. Battery information

The device is equipped with an integrated lithium-polymer battery. The battery cannot be replaced. Do not attempt to remove the battery from the device since it would damage the device. The full performance of a new battery is not achieved until after two or three complete charging-discharging cycles. The battery can be charged and discharged several hundred times, but it looses its capacity over time.

Disconnect the FBTHS01 from the power supply as soon as the battery is fully charged, overcharging would reduce the service life of the battery. A charged battery will lose its capacity if it is not used on a regular basis.

Important: Ensure that the battery is fully charged if you do not use the device for a long period of time. To avoid a complete discharge of the battery, the FBTHS01 should be charged at least every 3 months.

5. Charging the battery

The FBTHS01 is operated with a rechargeable battery. Charge the battery completely before its first use. Read the section "Battery information" before starting the charging process.

- 1) Connect the charger to the correct outlet.
- 2) When the charger is connected to the headset, the red indicator light will turn on. Charging the battery fully may take up to 2 hours.
- When the battery is fully charged, the red indicator light will turn blue. Disconnect the charger from the headset and the outlet. The headset is ready to use.
 NOTE:
- For first time use, please charge the headset fully.

- The fully charged battery has power for up to 27 hours of talk-time or up to 750 hours of standby time. However, the talk and standby times may vary when used with different

mobile phones or other compatible Bluetooth[®] devices, usage settings, usage styles, and environments. When the battery power is low, the headset will remind you by a "Beep" tone every 20 seconds, and the red indicator light starts to flash.

- For using the FBTHS01 with iPhone or Blackberry, an additional battery meter feature will be activated and the remaining battery capacity will display on your phone.



6. Pair to your Bluetooth® phone

Before you use your headset the first time, you must pair the unit with a Bluetooth[®] enabled mobile phone. Pairing is a one-time process and required only for the first connection with the cell phone The FBTHS01 can be paired with up to eight cell phones and be connected simultaneously with two cell phones.

- Keep the FBTHS01 within range of a Bluetooth[®]-ready cell phone; the distance should not exceed a meter.

- The headset must be turned off.

- Hold the On/Off button for approx. 5 seconds until you hear a short-low signal tone and the indicator light intermittently flashes red and blue. The device is in pairing mode. Pairing mode should engage automatically upon the first time turning on the headset.

- Find the Bluetooth[®] setting of your cell phone and start the search for Bluetooth[®] devices. (For further details,

please read the operating instructions of your cell phone). - From the list of devices found, select the "FBTHS01". - If required, enter the PIN code "0000" and confirm the entry. If the pairing process was successful, you will hear a signal tone and the indicator lights blue for 3 seconds. (Note: The PIN code is preprogrammed and cannot be changed.) - After pairing, the FBTHS01 automatically connect with the cell phone. For some cell phones, you have to manually confirm the connection. Once paired, the headset will change to standby mode and the indicator light will flash blue every 10 seconds.

Note: If pairing is not completed within 2 minutes, the headset will turn off. If this happens, repeat the pairing process.

7. Multi-connection function

The multi-connection function allows for the simultaneous use of the FBTHS01 with two cell phones. This is an advantage for users with a personal and a business cell phone.

Establishing a connection with two cell phones

There are several options of connecting the FBTHS01 with already paired cell phones.

- Automatic connection

When turning on the FBTHS01, a connection is automatically established with the two most recently connected cell phones.

- Establishing a connection via the FBTHS01

To manually establish a connection between the FBTHS01 and the two most recently connected cell phones, press the On/Off button. The FBTHS01 first connects itself with the most recently connected cell phone. Then it connects itself with the next most recently connected one.

- Establishing a connection via the cell phone

If the cell phone is not one of the two most recently connected cell phones with the FBTHS01, you have to establish the connection via the Bluetooth[®] menu of the cell phone. After successful connection, you can establish another connection with a second cell phone. This allows you to determine the sequence of connections. If two cell phones are connected with the FBTHS01, the cell phone connected first is the first device and the other one the second device. Another connection can be established only after first disconnecting one of the two cell phones. The cell phone that is still connected afterwards becomes the first device in the sequence.

Note that voice dialing is available only for the first device and the operation for redialing the last number differs for the first and the second device. The other functions are executed the same way using the FBTHS01 as a connection with only one cell phone.

8. Turning headset on /off

Turning on your headset

While the headset is turned off, press and hold On/Off for 3 seconds until you hear a tone from low to high. The headset is now on. The Blue indicator light will be solid for 2 seconds.

Connecting to a Bluetooth® phone

If your headset has completed the pairing process successfully, when the headset is turned on, it will connect to the phone you last connected with automatically. Please ensure your phone's Bluetooth® function is active.

Turning off the headset

At any working state after the headset is powered on, press and hold On/Off for 5 seconds. You will hear a tone from high to low, and the Red indicator light will be solid for 2 seconds. The headset has now powered off. Note:

To conserve power, if the headset is not connected to a device for approximately 10 minutes, the headset will turn off automatically.

9. Wearing your headset

According to your preference, you can wear the headset on your left or right ear. The adjustable head strap design allows for a comfortable fit.



10. Using the FBTHS01 Making a call

- Using phone's keypad

In standby mode, dial the number on your phone's keypad to make a call.

- Use Voice-Dialing

In standby mode, press the On/Off 3-4 seconds, you will hear a short tone from the headset, and the phone will prompt you to say the voice tag which you have already attached to your contact. If the voice tag is identified by the phone, the related number will be dialed. Please ensure that your mobile phone supports this voice dialing function, and voice tags have been set up on your mobile phone prior to attempting this. Refer to your mobile phone's user guide or contact your service provider.

Note: the voice dialing is available only for the first device if two cell phones are connected.

- Last number re-dialing

In standby mode, double press the On/Off button, The last number you dialed will be re-dialed.

Note: If two cell phones are connected with the FBTHS01, hold the Volume (-) button for 2 seconds to dial the last number of the cell phone connected previously.

Answering a call

When you receive an incoming call, press the On/Off button shortly to answer the incoming call; you can also answer the call directly from your phone.

Reject an incoming call

When you receive an incoming call, press and hold On/Off button for 3 seconds to reject the incoming call.

Transferring a call

While a call is in progress, press and hold Volume (+) for 3 seconds. The call will be transferred from your phone to

your headset. Repeating the operation can transfer the call from your headset back to your phone.

Ending a call

While on a call, press the On/Off button shortly to end the call; you can also end the call directly from your phone.

Call-waiting (Three-Way Calling)

Before using the Call-Waiting function on your headset, please ensure that your phone supports this Hands-free profile and you have access to the service by a wireless provider.

- If there is an incoming call while a call is in progress, press On/Off shortly. This will accept the waiting call and end current calling.

- If there is an incoming call while a call is in progress, press and hold On/Off for 3 seconds to accept the incoming call and place the current call on hold.

- While a call is on hold and you are engaged in an

additional call, press On/Off shortly to end the current call and resume the call holding.

- While a call is on hold and you are engaged in an additional call, press and hold On/Off for 3 seconds to shift the current call to hold and connect you with the previously held call.

- While you are engaged in one call with another call on hold, Double press Volume (-) button to add the held call to the current conversation to make a three-way call.

- While you engaged in a three-way call, double press On/Off to end all calls.

Volume control

While on a call, you can adjust the volume by pressing the Volume(+) and Volume(-)button or you can adjust the volume directly from your phone.

Mute

While a call is in progress press and hold Volume(-) button,

for 2s, you will hear a tone from low to high. The headset's MIC is now muted. You will hear a remindful tone every 10 seconds, notifying you that your MIC is still muted and a call is still in progress. Repeat the operation and you will hear the tone from high to low. The mute function is now cancelled.

Music streaming

The FBTHS01 supports A2DP profile that allows for wireless streaming of stereo music from a phone or other Bluetooth enabled music device. The music will pause automatically while a call is dialed out/incoming, and resume when the conversation has ended.

11. Reset the FBTHS01

The FBTHS01 can be paired with up to eight cell phones. You can delete the paring list and reset the headset to the factory settings by doing the following: - The headset must be turned on and not be connected to any cell phone or device.

 Press and hold the On/Off, Volume(+) and Volume(-) buttons simultaneously for approx. 5 seconds until the indicator light flashes red 3 times.

If the paring list was deleted, the headset will return to stand-by mode without connection.

12. Safety and general information

- 1) Please read this User's Manual carefully and follow all instructions.
- 2) To avoid any damage or malfunction of the device do not drop the device from high places.
- Keep device away from humidity, water and any other liquid. If the device is exposed to water, moisture and other liquids do not operate it to avoid any electrical

shock, explosion and damage to the device or yourself.

- 4) Do not place or keep this device near any heat sources, such as, direct sunlight, radiators, stoves or other apparatus that produce heat. This may cause an explosion, degrade the performance and/or reduce battery life.
- 5) Do not modify, repair or disassemble device (Especially the battery). Doing this will void the warranty.
- 6) Do not place heavy objects on the device.
- 7) Use only the supplied and approved chargers.
- 8) Please contact TD Electronics for replacement or support with this product.
- 9) Unplug this device when unused for long periods of time or during lightening storms.
- 10) The battery used in this device may present a risk of fire or chemical burn if mistreated.

13. FCC & IC Statement

Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. Note: The manufacturer is not responsible for ANY interference, for example RADIO or TV interference, caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment.

14. EC Declaration of Conformity

Operation is subject to the following two conditions: (1) This device may not cause harmful interference. (2) This device must accept any interference received, including interference that may cause undesired operation. Note: The manufacturer is not responsible for ANY interference, for example RADIO or TV interference, caused by unauthorized modifications to this equipment. Such modifications could void the user's authority to operate the equipment. This product is CE certified according to the provision of the R&TTE Directive (99/5/EC). This declares that this product is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. Please note that this product uses radio frequency bands not harmonized within EU. Within the EU this product is intended to be used in Austria, Belgium, Denmark, Finland, France, Germany, Greece, Ireland, Italy, Luxembourg, The Netherlands, Portugal, Spain, Sweden, and United Kingdom and within EFTA in Iceland. Norway and Switzerland.

WARRANTY

This FBTHS01 is under warranty for 12 months from the date of your purchase. All returns must be accompanied by proof of purchase.

Manufacturer warrants to original purchaser that the product finished hereunder shall be free from defects in material and workmanship under normal use and service. In the event of any defect in material or workmanship. the Manufacturer will for twelve (12) months from the date of delivery of product to purchaser, F.O.B. point of origin replace any defective parts in respect to the product or replace the product with new or like new product at Manufacturers option. In the event of a defect, return the product in tact to the Manufacturer (shipping to Manufacturer will be paid by purchaser) with evidence of purchase date within last 12 months for proper handling of the warranty claim.

What is Not Covered:

- Defects or damage resulting from use of products in other than it normal and customary manner
- Defective or damage from misuse, accident, water or neglect
- Scratches or cosmetic damage that does not affect operation of the product
- Product damage or bodily injury

General Provisions: This warranty is given in lieu of all other express warranties, implied warranties, including without limitation, implied warranties or merchantability and fitness for a particular purpose, are limited to the duration of this limited warranty, in no event shall the Manufacturer or seller be liable for damages in excess of the purchase price of the product

Falcon Electronics

3000 Custer Rd, Ste 270-542, Plano TX 75075

972.600.1320 · www.dashcam.co