

# Gas Station LED Canopy Light Installation Guide

## Cautions:

1. Can not use the electric generator to test the LED lamp.
2. Please abide by related country, regional and local law and regulations when install this fixture.
3. Please turn off the power before installation or maintenance.
4. Proper earth grounding is required to ensure safety.


## Notice:

1. To avoid possibility of electrical shock or fire, the installation personnel must have professional electric knowledge.
2. Please wear gloves to avoid injury before installation.
3. If any smoke or spark of the wire happened, please turn off the power immediately and notify relevant personnel.

## Attention:

1. Please check if there is any damage during shipping. If so, please contact manufacturer timely.
2. Please read the installation instruction carefully to check whether all the accessories are complete. After confirmation, then install the fixture according to installation steps.
3. The installation of the product can be used when it is marked with "√".

## Wiring Diagram:



## Installation Method I

1. Fix the safety rope on the back of fixture (Figure 1).
2. Drill the alignment holes on the top ceiling, make them match to the holes on fixture (Reference supplied screws for diameter of holes (Figure 2)).
3. Insert the supplied rubbers into the alignment holes, lock the safety rope on the ceiling. Make wiring connections per "Electrical Connections" section and make sure the good wire protection.
4. Mount the fixture on the ceiling by supplied screws (Figure 3).




Figure 1




Figure 2




Figure 3

## Installation Method II

1. Connect the wiring to the local power supply in the 3/4" NPT Stem (Figure 4).
2. Screw the fixture to the 3/4" NPT Stem (Figure 5).




Figure 4




Figure 5

## Installation Method III

- I: 1. Fix the mounting bracket on the back of fixture by supplied screws. (Figure 6)
2. Unscrew the nut from customer supplied 3/4" NPT stem, make the stem hole on mounting bracket through 3/4" NPT stem, then screw the nut back to 3/4" NPT, and fix it. (Figure 7)
3. Make wiring connections per "Electrical Connections" section and make sure the good wire protection.




Figure 6




Figure 7

- II: 1. Drill the alignment holes on the top ceiling, make them match to the holes on mounting bracket. (Figure 8)
2. Insert the supplied rubbers into the alignment holes, then fix the mounting plate on the ceiling by supplied screws. (Figure 9)
3. Mount the fixture on the mounting plate by supplied screws. (Figure 10)
4. Make wiring connections per "Electrical Connections" section and make sure the good wire protection.




Figure 8




Figure 9




Figure 10

## Warning / Avertissement

MIN 75°C SUPPLY CONDUCTOR

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.

LES FILS D'ALIMENTATION 75°C MIN

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS.