ASE-DK075 Fixed Station Terminal for Iridium 9555 Handsets





Introducing the ASE Docking Station that transforms the Iridium 9555 Phone

Applied Satellite Engineering's ASE-DK075 docking station offers unprecedented reliability, superior intelligence, and rugged integrity to make an exceptional phone even better. Together, the Iridium 9555 and the ASE-DK075 offer an unsurpassed package of reliability, innovation, power and efficiency.

The ASE-DK075 provides office, vehicle and vessel customers with a dependable and critical lifeline via Iridium Satellite Network. The mobile satellite service, which offers the only pole-to-pole global communication coverage, enables the ASE-**DK075** to provide unfaltering satellite communication anywhere on Earth.

The docking station's advanced ergonomic design, small footprint, and array of attractive and up-to-the minute safety features place the ASE-DK075 into a league of it's own.



Applied Satellite Engineering is a global leader in the manufacture of satellite communication equipment. The Company is an Iridium Value-Added Manufacturer and is widely hailed for its quality workmanship, integrity and ability to anticipate customers' needs with landmark solutions.

ASE-DK075 Features And Equipment

RJ11 Connection and PBX Integration Connects to an analog phone (single or PBX) including multi-handset wireless phones. Use of a cordless phone with expandable headsets can provide up to eight units within a two-mile range (unobstructed) from the base station. Or integrate a Satellite line into your company's PBX phone system.

Enhanced Smart Dial includes ground-breaking safety and problem-solving features It is the only docking station that can detect the correct format for the country that is being dialed and place the call once the number is entered. Specific audio tones alert the user when satellite is out of sight or signal strength is low, if phone is undocked and even when payment for service is overdue. The Smart Dial indicates when something's wrong, and how to correct it.

Innovative and Ergonomic Design Rugged and secure locking restraint secures 9555 in cradle in any environment. Technology for your control room, but attractive enough for your stateroom.

Status Indicators for Simple Operation – Large icons enable status viewing from 25 feet combine with the Iridium handset's graphic display for set-up, troubleshooting, programming and operation.

Indoor/Outdoor Dock the Iridium phone in our docking station to access satellite communication indoors. For outdoor use, un-dock the handset and take it with you.

Simple Installation Electronics-inclusive cradle means no extra components to hide which keeps installation simple and uncluttered.

<u>USB Connect</u> Serial port for data connections including Internet connect with Direct Internet 2.0. Allows the user to dial up the Internet to access email, weather reports and other information from a laptop.

♦ Built in Charger

- ♦ Base Station Ringer
- ♦ Handsfree Operation
- Vide-range Power Input
- ◊ Multiple Antenna Options ◊ PBX Integration Experts
- ♦ Ideal for Corporations, resilience and emergency preparedness, and mid-to-large maritime vessals

Remote Satellite Systems

INTERNATIONAL

An expanding family of products provides cost and features for every Price Point





ASE-DK075 Fixed Station Terminal for Iridium 9555 Handsets







9555 Docking Station Interface Ports
PORTPORTFUNCTIONA) Mini USBUSB Data InterfaceB) RJ-11PBX / Analog Phone ConnectionC) RJ-45Iridium Intelligent HandsetD) Power Input9-36 VDC Voltage InputE) Reset ButtonInitiates a System Reset

Mechanical Specifications		
PARAMETER	VALUE	
Dimensions	9.75" x 5.50" x 3.25" (LxWxH)	
Weight	1.4 lbs	
Mounting	Direct wall mount or Universal Mounting (see accessories)	

Ordering Information		
PART NUMBER	DESCRIPTION	
ASE-DK075	9555 Docking Station with RJ-11.	
ASE-MNT01	Docking Station Universal Mounting Kit	

Accessories

: iridium





Iridium Antenna Specifications		
PARAMETER	VALUE	
Operating Temperature Range (without loss of function)	- 40°C to + 85°C	
Measurement Frequency Range	1616 MHz - 1626.5 MHz	
Return Loss (minimum)	9 .5 dB (< 2:1 VSW R)	
Gain (weighted average minimum)	0.0 dBic	
Minimum "Horizon" Gain	- 2.0 dBic (82 degree conic average)	
Nominal Impedance	50	
Polarization	Right Hand Circular (RH CP)	
Basic Pattern	Omnidirectional and Hemispherical	
Note : The entering apple must ensure a loss of < 2 dP and		

Note : The antenna cable must ensure a loss of < 3 dB and the minimum link margin of 12.1 dB must be maintained.

Electrical Specifications		
PARAMETER	VALUE	
Operating Voltage Range	9 – 36 VDC unregulated	
Power Consumption	12 watts peak	

Environmental Specifications		
PARAMETER	VALUE	
Operating Temperature Range	– 15°C to + 70°C	
Exposure	Dry, protected location per IEC 60945	



TOLL FREE 1-888-989-8199

1455 N. Dutton Suite A, Santa Rosa, CA 95401 FAX 707-546-8198 • info@remotesatellite.com www.remotesatellite.com

