

## INSTALLATION INSTRUCTIONS

**WARNING:** BE SURE THE ELECTRICITY TO THE WIRES YOU ARE WORKING ON IS SHUT OFF; EITHER THE FUSE IS REMOVED OR THE CIRCUIT BREAKER IS TURNED OFF. TURNING THE POWER OFF USING THE LIGHT SWITCH IS NOT SUFFICIENT TO PREVENT ELECTRICAL SHOCK.

NOTE: The important safeguards and installation instructions appearing in this guide are not meant to cover all possible conditions or situations that may occur. It must be understood that common sense, caution, and care, are factors which cannot be built into any product. These factors must be supplied by the person(s) installing this unit.

## READ & SAVE THESE INSTRUCTIONS

CAUTION: If you feel you do not have enough electrical wiring experience, either refer to a do-it-yourself wiring handbook or have your lighting fixture installed by a qualified, licensed electrician.

### UNPACK THE PACKAGE

**Check the contents to be sure everything is included**

Tools Needed: Personal Protection equipment, Screwdriver, Step ladder, Wire cutters, wiring supplies as required by electrical code.

### INSTALLATION & OPERATION INSTRUCTIONS GENERAL

Before starting the installation, disconnect the power by turning off the circuit breaker or by removing the appropriate fuse at the fuse box. **Turning the power off using the light switch is not enough to prevent electrical shock.**

All electrical connections must be in accordance with local and National Electrical Code (NEC) standards. If you are unfamiliar with proper electrical wiring connections, obtain the services of a qualified electrician.

Remove the fixture and the mounting packages from the box and make sure that no parts are missing by referencing the illustrations in the installation instructions.

Be sure to read these installation instructions and review the diagrams thoroughly before installation.

For any questions regarding your light fixture contact us via email  
[support@westninthvintage.com](mailto:support@westninthvintage.com)

## West Ninth Vintage Single Wood Flushmount Light Fixture Installation Instructions

All West Ninth Vintage Light fixtures are manufactured to be installed to a standard round junction box. The instructions are written to start with a pre-existing junction box that is controlled by a switch. All West Ninth Vintage light fixtures are dimmer switch compatible. For the best results be sure that the light bulbs used are also dimmer switch compatible.

1. Remove all items from their packaging.
  - a. Light Fixture



- i.
  - b. Mounting hardware – both items are attached to the back of the fixture
    - i. Crossbar – attached to light socket
    - ii. Wire nuts – in bag attached to wires
    - iii. Screws – in bag attached to wires
2. Remove the wire tie holding the hardware to the wires
3. Connect the wires and connect to main power using the wire nuts. Do not shorten the wires. This will caused too much strain on the wires when they are installed.
4. Remove the Crossbar from the base of the socket and mount to the junction box
5. Push the excess wire into the crossbar so that the base of the socket can touch the crossbar without any wire interfering
6. **Turn the socket at least six (6) full turns counter-clockwise (to the left) and then attach to the crossbar by turning to the right. *Turning to the left minimizes the tension from the wires when it is fully installed. This is an important step. Failure to do this could cause the fixture to fail.***
7. Align the fixture in the direction desired before the final turn of the socket
8. Loosen the screws from the cage and fit around the socket. Tighten the cages using screws.
9. Reconnect the power to the circuit (breaker or fuse)
10. Install your light bulbs and enjoy!

For any questions, please contact us at [support@westninthvintage.com](mailto:support@westninthvintage.com)