Instruction to Upgrade Firmware on Your NVR System



W-NVR

CVT808N

N6952326527131

9013160200

3. 0. 3. 1

2019-04-29 09:21:09

Https://www.cvtus.com

Confirm Your NVR Firmware Version Before Starting

To Confirm the Current Version

2

3

Navigate to 'System Settings' in the NVR Menu and Click on 'System'

Only the Following Versions Can Be Upgraded

CVT808N FIrmware Ver. 3.0.3.1 Built Time : 2019-04-29 (No Monitor Model)

CVT808A FIrmware Ver. 3.0.3.1 Built Time : 2019-04-29 (w/Built In Monitor Model)

Checking the firmware version is essential for stable system operation

| System | |
|--------|--|
| | |
| | |

vided by device manufacturers can improve performance and fix critical securit

Download File from the Link

For CVT808A FIrmware Ver. 3.0.3.1 (w/Built In Monitor Model)

FWHI36D_20200619_W-NVR_CVT808A_3_0_8_0_9013160200.rom

For CVT808N FIrmware Ver. 3.0.3.1 (No Monitor Model)

FWHI36D_20200821_W-NVR_CVT808N_3_0_8_3_9013160200.rom

)SJG0

are

are



| 100 00 | ~ |
|---|---|
| ile system | |
| FAT32 (Default) | ~ |
| llocation unit size | |
| 4096 bytes | ~ |
| | |
| olume label | |
| Format options | |
| olume label Format options Quick Format | |
| olume label Format options Quick Format | |

Transfer New Firmware from Your PC to the USB Drive

Format Your USB Drive with the FAT32 File System

Save the Firmware in the Root Directory, Not in a Subdirectory.



Insert Your USB Drive into Your NVR



Navigate to System Setup > System > System Upgrade > Local Upgrade in Your NVR



Click 'Local Upgrade' to Begin the Upgrade Process.

Your NVR System Will Reboot After Completion