




GRAPI

User Manual

Product structure:

1.Blue light 2.Power switch 9.White light 3.Play/Pause buttor 10.USB port 4.PREVIOUS/VOL 11.AUX port 5.Power indicator (4 sections) 12.TF port 13.Type-C charging port



(P1T1)



Bluetooth Speaker X

Microphone x

1. Long press the power switch for 2 second 8.EQ button to turn on, the LED indicator flashes blue.

Power ON/OFF

- 2. Long press the power switch for 2 seconds to turn off, the LED status indicator goes off
 - 3. Double press the power switch, the power indicator lights up (30 seconds each time)

- waiting for the speaker to be paired.
- 2. Then turn on the Bluetooth of your phone and search for "iGear Grape". Click manually to connect. If the connection is successful, the LED indicator will stop flashing
- 3. The speaker can automatically reconnect to the last paired device. So when the Bluetooth of your device turns on. (Just turn on the speaker), it will automatically reconnect.

Answer incoming calls

Redial call

- to reject the incoming call.
- TF card mode
- Press the play/pause button to end the ongo

Bluetooth connection

- Turn on the Bluetooth speaker, the LED Press the play/pause button twice to redial th indicator flashes blue continuously while
 - Bluetooth disconnection Long press the play/pause button to disconnect the Bluetooth connection

Press the play/pause button to answer incoming calls.

Reject Incoming calls Mode switching

Long press the play/pause button for 2 seconds Short press the power button to switch between different modes

AUX mode Connect your music player/smartphone to the

Simply insert the USB drive into the USB slot

USB mode

the speaker it will switch to the AUX mode

Light Modes

Short press the light mode button to switch or and the device will automatically recognize the the light effect (there are 8 different lighting USB drive and play the music stored in it effects.) press the ninth time to turn off the

Voice Assistant

Long press the Light mode button to activate

Equalizer mode

Short press the EO mode button switch between normal and Bass boost sound effect

seconds to clear pairing records, restore Simply insert the TF card into the TF card slot the default volume and prompt tone, and and the device will automatically recognize the automatically shut down TF card and play the music stored in it.

pause/plav: speaker with the 3.5mm AUX cable provided 2. Long press the "-"for PREV in the box and short press the power button or 3. Long press the "+"for NEXT

True Wireless Stereo (TWS)

You can connect two "iGear Grape" speakers a a pair for stronger stereo and surrounding . Make sure the Bluetooth is OFF on your

smartphone/media player;

- 2. Turn on two iGear Grape speakers: 3. Press the EQ mode button twice on both
- the speakers and a prompt sound will appear Directions to play music which means both speakers are now In TWS 1. Short press the play/pause button to mode.
- 5. Short press the "+"for VOL+

Long press the EQ mode button for 6

- 4. Then turn on the Bluetooth of your phone

4. Short press the "-"for VOL -

Power Bank

charging smartphones and other devices over USB cable (Input voltage: 5V/IA). If the Bluetooth function of the speaker is not turned on, the speaker can only charge other electronic devices for 30 minutes, and then automatically turn off

- As the product has a built-in non-removeable and rechargeable battery, we recommend to
- 2. The power LED lights up red while charging and goes off when charging is complete

- Input voltage: DC5V/2.4A (max)
- and search for "iGear Grape". Click manually to connect.

Speaker also double as power bank for

- Support: BT. AUX. TWS. TF. SD. MIC. Hands-Free calls
- use the Type-C cable provided with the speaker Charging port: Type-C
 - Product size: 342cm X 11.5cm X 18.7cm

Specifications

Rated power: 70W

Tweeters: 31mm X 2

Charging time: 5Hrs

Bluetooth version: V5.3

Speaker frequency: 80Hz-18KHz

Play time: Upto 18Hrs (50% Volume)

Speaker drivers: 79mm X 2

IPX6 Waterproof

Material: ABS+Fabric

Input voltage: DC5V/IA

Charging Port: Type-C Product size: 24.6 cm x 5.2cm

Use for the first time:

Turn on the Bluetooth speaker first, press and hold

the light mode button for about 3 seconds, then turn on the microphone, and press the Power button on the microphone 3 times. Once the connection is successful, the speaker and the microphone will be automatical paired for the next time use.

Microphone Specifications

Battery: 3.7V/1800mAh

Microphone Mode

Play time: 4-5 Hours (Medium volume)

Charging time: 2-3 Hours

Wireless working range: 15M (without obstacles) Volume increase Volume decrease

MIC Functions

Ech- Short press

Warranty period: 1 Year In case of consumer complaints

i. Please follow the instructions to operate.

Eliminate the original sound of v

in music

Super echo

Karaoke function

. Please charge the product with input power of or below 5V/2.4A, in order to protect the battery

Precaution

- 3. In case of any malfunction, press and hold the
- play/pause button for 8 seconds to automatically reset the machine

stoves, or other heat generating instruments

- 4. Please store or use the product in a normal temperature environment.
- 5. Please keep the product away from heat source, such as radiators, hot air regulators
- 6. Don't iam the ports of the product, such as
- charger port, LED port and microphone etc.

Warranty

Customer Care - +91 9372667193 Email: sales@igear.asia

www.igearworld.com

voice assistant.