



# ***Make A Wake Marine***

## T-Top or Tower LED Light Bar Installation



1. Begin by unpacking all components from the box and ensure that all parts have arrived intact.



2. Identify the small black clamp adaptor along with two small bolts. Utilize the supplied allen wrench to securely fasten the small bolts into the nuts already installed in the LED light bars.



3. Before fully tightening the small allen bolts, position the large nut behind the black clamp adaptor. This step is crucial as it won't be feasible to fit the nut in afterward. Tighten the small allen bolts securely.



4. Locate the large bolt, washer, and lock washer. Insert the bolt through the bottom half of the clamp into the large nut placed behind the small black clamp adaptor. Tighten this clamp securely.



5. Following the tightening of the clamp, determine the appropriate rubber configuration based on the diameter of the tubing. For 2.5" tubing, no rubber inserts are necessary. For 2.0" tubing, use one set of rubber inserts inside the clamps. For 1.5" tubing, use both rubber inserts, ensuring to trim approximately 1" from the inner rubber clamp and removing the grooved sides for a proper fit.



*Rubber installation for 1.5" Diameter tubing.*



*Rubber installation for 2.0" Diameter tubing.*

6. Install the other half of the clamp and tighten it in place.



7. All LEDs from Make A Wake Marine are designed for marine 12V applications. It's imperative not to connect them to any other power source, as it may damage the LED lights.

8. It is highly recommended to install the LEDs on a fused switch. Most boats come with extra/accessory factory-installed 12V fused switches on the dashboard.

9. Utilize waterproof connectors on all wiring connections to ensure durability and safety.

10. Should you encounter any questions or require assistance during the installation process, please don't hesitate to contact Make A Wake Marine for support.

Following these steps will ensure a smooth and successful installation of Make A Wake Marine's 6.5" LED Spreader Lights or 23" LED Light Bar on your Wakeboard Tower or T-Top.