

Type _____

Project _____

Catalog No. _____

Lamp/Wattage _____

NTH-132 / NTH-133

Belgium™ Die-Cast PAR Front Loading Gimbal

Lamp: 75W PAR30 (NTH-132) / 90W PAR38 (NTH-133)

PRODUCT DESCRIPTION

Line voltage front-loading gimbal fixture. Heavy die-cast construction provides superior strength, rigidity, and heat dissipation. Locking front ring protects lamp and enhances appearance. Front loading capability provides quick, easy lamp maintenance with minimal interference with original fixture aiming.

FEATURES

- Heavy die-cast construction
- Die-cast Lamp Locking Ring
- Fully adjustable, firm angle position
- High-strength stainless steel electrical contacts
- One or two circuit track capable

CONSTRUCTION

Housing

0.09" Die-cast aluminum two-piece housing with modernistic detail secured together with finished Allen-head screw. Two arms constructed from thick 0.050" die-cast aluminum extend from the housing and contain molds to secure 0.25" die-cast aluminum locking ring.

Structural Arm

0.10" "L" Steel bracket connects fixture housing to electrical contact head. Two finished plastic knobs allow user to lock fixture position to desired angles.

Socket

Porcelain jacketed aluminum screw thread medium-base socket.

Wiring

Teflon coated wire leads connect socket and housing to electrical contact head. Teflon coating is durable and resists heat degradation from lamp and housing radiation.

Lamp

NTH-132: 75W PAR30 Maximum (not included)
 NTH-133: 90W PAR38 Maximum (not included)

Contact Head Assembly

"H" Style (standard): Three 0.030" stainless steel contacts mounted in premium plastic housing.

"J" Style: Two contacts and ground contact mounted in premium plastic housing with on/off switch.

"L" Style: Two contacts and ground contact mounted in premium plastic housing.

Finishes

Black, Silver, or White heat-rated powercoat. Custom painting or anodizing for special applications are also available. Custom finishes will require lead times that vary depending on vendor schedule. Please consult factor for quotation, and provide either a Dunn Edwards number or color chip for exact matching.

One/Two Circuit Conversion

Positive contact (opposite neutral and ground contacts) is preset to "down" position at the factory, but may be raised to the high position to install onto the second circuit of Nora Lighting's NT-2300 series two-circuit track.

Compatibility

H-Style is compatible with Halo or any other brands configured to Halo 3 (single circuit) or Halo 4 (2 circuit) track system design.

J-Style is compatible with "J" Style track.

L-Style is compatible with "L" Style track.


Note: fixtures may not be compatible with non-Nora monopoint adapters.

Listing

UL Listed as track lighting fitting




ITEM NUMBERS



NTH-132 Dimensions:

Diameter: 4-1/4"
 Length: 5-1/8"
 Max. Ext.: 9-3/8"

- NTH-132B:** Black Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, H-Style
- NTH-132B/J:** Black Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, J-Style
- NTH-132B/L:** Black Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, L-Style
- NTH-132S:** Silver Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, H-Style
- NTH-132S/J:** Silver Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, J-Style
- NTH-132S/L:** Silver Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, L-Style
- NTH-132W:** White Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, H-Style
- NTH-132W/J:** White Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, J-Style
- NTH-132W/L:** White Belgium™ Die-Cast PAR Front Loading Gimbal PAR30, L-Style



NTH-133 Dimensions:

Diameter: 5-3/8"
 Length: 6-3/4"
 Max. Ext.: 10-1/2"

- NTH-133B:** Black Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, H-Style
- NTH-133B/J:** Black Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, J-Style
- NTH-133B/L:** Black Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, L-Style
- NTH-133S:** Silver Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, H-Style
- NTH-133S/J:** Silver Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, J-Style
- NTH-133S/L:** Silver Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, L-Style
- NTH-133W:** White Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, H-Style
- NTH-133W/J:** White Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, J-Style
- NTH-133W/L:** White Belgium™ Die-Cast PAR Front Loading Gimbal PAR38, L-Style