NTLE-265 (Versa Series)

MR16 Single Head Track Fixture.

Lamp : 3W-50W MR16 (Not Included)

PRODUCT DESCRIPTION

Low voltage die cast aluminum designer cube fixtures with integral transformer/driver. Compatible with several LED MR16 lamps as well as halogen MR16 lamps.

FEATURES

- · Compatible with several LED MR16 lamps or halogen MR16 lamps (not included)
- Die cast aluminum provides superior strength and rigidity.
- Low profile, aesthetic design.
- High-strength stainless steel electrical contacts.
- One or two circuit track capable.

CONSTRUCTION

Track Head

Die cast aluminum construction. All edges are softened for aesthetic appearance

Contact Head Assembly

"H" Style (standard): Three 0.030 stainless steel contacts mounted in premium plastic housing.

"J" Style: Two contacts and ground contact mounted in premium plastic housing with on/ off switch.

"L" Style: Two contacts and ground contact mounted in premium plastic housing.

ELECTRICAL SYSTEM

Input voltage - 120V/60Hz Input

Output voltage - 60VA Max. Load

<u>Transformer</u> - Solid state LED Driver provides noise-free voltage reduction and operation. If dimming, use electronic low voltage rated only dimming controls. <u>Wiring</u> - Teflon coated wire lead connects socket and housing to electrical contact head. Teflon coating is durable and resists heat degradation from lamp and housing radiation. <u>Socket</u> - Porcelain socket for GU5.3 12V MR16 lamp.

Lamp

3W-50W 12V MR16 LED lamp
 50W 12V MR16 Halogen w/ Lens lamp
(Ordered Separately)

<u>One/Two Circuit Conversion</u> - Positive contact (opposite neutral and ground contacts) is preset to "down" position at factory but may be raised to the higher position to install onto the second circuit of Nora Lighting NT- 2300 series two-circuit track.

FINISHES

Black or White heat rated baked enamel paint.

LABELS AND LISTINGS

UL Listed.



Versa Single-Head Track fixture with Dimmable Integral Electronic Driver/Transformer

Catalog No.	Finishes	Style
NTLE-265	$\mathbf{B} = Black$	Blank = H-Style
	$\mathbf{W} = \mathbf{W}$ hite	/J = J-Style
		/L = L-Style

Create a complete track head number: Example: NTLE-265B Versa Single-Head Track fixture with Dimmable Integral Electronic Driver in black finish.

ENORALIGHTING.

Туре

Project

Catalog No.

Lamp/Wattage

DIMENSIONS



6505 Gayhart St., Commerce, CA 90040 • Phone: 800.686.6672 • FAX: 800.500.9955 • www.noralighting.com e-mail: nora@noralighting.com • Specifications subject to change without notice. © 2014