



200 Amp Pagoda to 19-Pin Receptacles

100A 120/208 VAC, (1) Set of (5) 16 Series Cam-type, Single Pole Males (Plugs) to (4) LSC19 19-Pin Receptacles and (3) NEMA 5-20 (Edison) Duplex Receptacles, Pagoda

Part Number	DBS200-A4BM2
Markets	Entertainment
Rating	Indoor
Enclosure	Box
Input	Cams
Output	19-PinNEMA
Amperage	200A
Certifications	

Features & Benefits

- Fed from a panel or generator, this box provides overcurrent protected power for four multi-cable connections
- This box is typically used with multiple non-dimmed circuits.Provides four outputs for industry standard 6-circuit lighting multi-cable in addition to three duplex receptacles for convenience power
- Heavy-duty molded rubber enclosure is fully insulated and resistant to shock, impact and corrosion
- Circuit breakers are mounted under hinged lid for enhanced protection
- Stackable and compact for easy storage and convenient portability
- Elevated base keeps receptacles above ground level
- Reverse neutral and ground option helps prevent mis-mating for enhanced safety

Markets Served

Concert Touring, Theatrical, Live Events

Technical Information

Rating:	200A
Environmental Rating:	NEMA Type 1 (Indoor Use)
Input:	(1) set of (5) 16 Series Cam-type, 400 Amp, single pole, 600V, color-coded, plugs, 1.5 pigtails
Feed Thru:	None
Output:	(4) LSC19 19-Pin, 20 Amp, 2-Pole, 3-Wire, 125 VAC receptacles, panel mount; (3) NEMA 5-20, 20 Amp, 2-Pole, 3-Wire, 125 VAC, duplex receptacle, panel mount
Overcurrent Protection:	(27) 20 Amp, 125 VAC, single pole, hydraulic magnetic, branch-rated circuit breakers
Enclosure Type:	Pagoda

Dimensions:	14.25"L x 14.25"W x 14.15"H
Weight:	39.0 lbs
Agency Approval:	cULus Listed