## **LED A19 BULB 9W**

C&C Lighting Inc. Technical Data Sheet





- The LED A19 bulb replaces up to 60 watts traditional bulbs with only 9 watts usage
- It gives high output of the light with lower energy consumption
- It comes with dimmable function and long lifespan

## **TECHNICAL SPECIFICATION**

POWER	9W	9W
VOLTAGE	120V 60Hz	120V 60Hz
CCT	3000K	5000K
LUMEN	800Lm	800Lm
DIMMABLE	Yes	Yes
BEAMING ANGLE	300°	240°
TEMPERATURE RANGE	-20~45°C	-20~45°C
FEATURE	<ul> <li>Sustainable for damp locations</li> <li>Not for use in totally enclosed unminaries</li> </ul>	

## CAUTION

To avoid early failure due to incompatibility please observe the following precautions

This device is not intended for use with emergency exit fixtures or emergency exit lights

To avoid electrical shock, turn off the power before replacing bulbs

This lamp may not be compatible with all dimmers, occupancy sensors, or timers. For more dimmer information, please visit www.ccrlight.com

Do not use in totally enclosed luminaries or where directly exposed to weather.

This product is compatible with photo-controls, motion sensors or timing devices

## WARRANTY

This light bulb is warranted to perform free from defects for three years. If it fails to do so, you may return it with proof of purchase to 400 Esna Park Dr., Unit 11, Markham, ON. L3R 3K2 for replacement

