

# L1AW

## **GPS Active Antenna**

### **DESCRIPTION**

The L1AW is a high performance L1 Band active antenna suited for applications requiring low noise and excellent gain. The product functions to specifications over the entire operational voltage and temperature range at a minimal current draw. It includes high frequency selectivity to avoid interference with other nearby transmitters.

Built to support the wireless market, the precise L1 Band Active antenna features low noise and high gain to provide optimum signal quality.

#### **FEATURES**

- Outstanding Noise Figure < 1dB</li>
- Excellent Typical Gain of 33dB
- Wide Voltage Range of 3VDC to 16VDC
- Tiny Current Draw < 20mA</li>
- Bottom or Pole Cap Mount
- Multiple Connector Options

#### **OPTIONS**

The L1AW comes with many available options to meet specific needs. Please contact GPS Source via phone, email, or visit the website for further information on product options and specifications.



# 1 L1AW Specifications

Table 1-1. Electrical Specifications


Operating Temperature -40°C to 85°C

Parameter		Conditions	Min	Тур	Max	Units	
Frequency Range (Passband)		Ant: Output, VDC = 3V to 16V, Output = $50\Omega$	1560	1575	1590	MHz	
Out Impedance				50		Ω	
Gain	Element	Ant Element		3	3.5	dBiC	
	LNA	LNA, VDC = 3V to 16V, Output = $50\Omega$	32	33	35	dB	
Output SWR		VDC = 3V to 16V, Output = $50\Omega$			2.5:1	_	
Noise Figure		VDC = 3V to 16V, Output = $50\Omega$		0.8	1	dB	
Required DC Input Voltage		DC Input on RF Output Center Conductor	3		16	VDC	
LNA Current		Output = 50Ω, 5V		17	20	mA	
Rejection	+/-50MHz > 24dB	Ant: Output, VDC = 3V to 16V, Output = 50Ω	-22	-24	-25	dB	
	+/-100MHz > 35dB	Ant. Output, VDC – 3V to 16V, Output – 30s2	-34	-35	-37		
Polarization		Right Hand Circular					

## 2 Performance Data

## 2.1 Far Field Patterns — 1575MHz

Figure 2-1. Far Field Plots Rotating Linear







Figure 2-2. Far Field Plots Azimuth Cuts



# **3 Product Options**

Table 3-1. L1AW Available Options

Available Options								
Power Source Voltage	Voltage Input	Туре						
Power Source Voltage	DC 3VDC to 16VDC	Input on Center pin of RF Connector.						
	Туре	Limitations						
RF Connector	N Female	N/A						
Kr Connector	SMA Female	N/A						
	TNC Female	N/A						
RF Mounting	PM - L-Bracket Pole Mount Hardware (Pole is not included.)	See Figure 3-1.						
N. Mounting	PCM - Pole Cap Mount Hardware (Pole is not included.)	See Figure 3-2.						
Lightning Protection	DC to Ground on the Antenna Element	N/A						


Figure 3-1. (PM) L-Bracket Pole Mount



Figure 3-2. (PCM) Pole Cap Mount



### 4 Product Code Decoder




Notes: 1. Contact GPS Source for additional connector options.


- 2. To have product/part codes customized to meet exact needs, contact GPS Source at GPSS-Sales@gd-ms.com or visit the website at www.gpssource.com.
- 3. \* Lightning Protection option not available when choosing the Pole Mount option.


## 5 Mechanical Drawing

### 5.1 L1AW GPS Active Antenna




RECOMMENDED MOUNTING PATTERN





Notes 1. SHOWN WITH:

- ► TYPE N FEMALE RF CONNECTOR
- 2. AVAILABLE CONNECTOR OPTIONS
  - ► SMA FEMALE
  - ► TNC FEMALE



ISOMETRIC VIEW FOR REFERENCE ONLY

01/20/2016 Revision 001

GPS Source Part No.	Finish	Size	Mass	Tolerances	
L1AW	N/A	С	0.25lbs	Linear	Angular
Description	Material	3 <sup>rd</sup> Angle Projection		$.X = \pm 0.100$	±1°
L1A ANTENNA N(F) G = 33dB, NF = 1.2 dB 3-16VDC	SEE BOM	<b>(4)</b>		$.XX = \pm 0.050$ $.XXX = \pm 0.005$	RADII See Linear

Dimensions are in inches unless otherwise specified. IAW ASME Y14.5M - 1994





**L1AW Data Sheet** 

059-FAN-AAQ-XWX-RXZ-004 Page 8 of 8, 01/14/2020 2121 Executive Cir., Ste 100 Colorado Springs, CO 80906 Phone: (+1)(719) 421.7300 Toll Free: (+1)(866) 289.4777

GPSS-Sales@gd-ms.com www.gpssource.com

AS9100 and ISO 9001 Compliant Company





© 2016 GPS Source, Inc. All rights reserved.

GPS Source, Inc., GPS Live Inside, GPS Source logo, and other GPS Source, Inc. products, brands, and trademarks mentioned in this document are property of GPS Source, Inc. and/or its affiliates in the United States and/or other countries. Other products, brands, and trademarks are property of their respective owners/companies. Any rights not expressly granted herein are reserved.

DISCLAIMER: The materials in this document could include inaccuracies or typographical errors and are subject to change at any time. The materials are provided "as is" without warranty of any kind. To the maximum extent permitted by applicable law, GPS Source, Inc. and its suppliers hereby disclaim all warranties, either expressed or implied, and conditions with respect to the materials, their quality, performance, suitability, merchantability, fitness for a particular purpose, title, and non-infringement. LIMITATION OF LIABILITY: IN NO EVENT WILL GPS SOURCE, INC. AND ITS SUPPLIERS BE LIABLE FOR INDIRECT, SPECIAL, INCIDENTAL OR CONSEQUENTIAL DAMAGES, WHETHER IN AN ACTION OF CONTRACT OR TORT, ARISING OUT OF THE USE OR INABILITY TO USE THE MATERIALS AVAILABLE IN THIS DOCUMENT, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN PARTICULAR AND WITHOUT LIMITATION, GPS SOURCE, INC. SHALL HAVE NO LIABILITY FOR ANY LOSS OF USE, DATA, INCLUDING THE COSTS OF RECOVERING SUCH DATA, OR PROFITS.