#### **GENERAL DYNAMICS**

Mission Systems



# **MRPA-3SA**

## Horizon-Nulling GNSS Active Antenna, Side Mount

#### **Description**

The MRPA-3SA is a professional grade, active Horizon-Nulling GNSS antenna designed for long term reliability. Based on the acclaimed GNSS antenna base model, the MRPA is designed to null terrestrial interferences arriving at low elevation angles.

Designed to support the Warfighter, the portable, yet precise GNSS antenna is built for tough applications. The radome is made of a high-grade polymer, with a design to protect from UV, rain, lightning, chemical, and jet fuels. The MRPA-3SA is available with a side mount connector and multiple colors (per FEDSTD-595B).

#### **Features**

- Military and Civilian Applications
- GNSS Bands:
  - GPS L1, L2, L5
  - GLONASS L1, L2, and L3
  - GALILEO E1, E5, E6
- Waterproof
- Improved gain at zenith over standard FRPA
- Minimum 20 dB of rejection at 10 to 20 degree elevation angles

#### Options

The MRPA-3SA comes with many available options to meet specific needs. Available product options are listed on Page 3.



MRPA-3SA-SF



### **MRPA-3SA**

#### 1 MRPA-3SA Specifications

# **Table 1-1. Electrical Specifications**Operating Temperature -54 °C to 71 °C

Parameter		Conditions	Min	Tues	Max	Units
raranieter		Conditions	IVIIN	Тур	iviax	Units
Frequency Range (Passband)	GNSS Upper Band	Ant: Output: 50 Ω	1559	1575.42	1610	MHz
	GNSS Lower Band		1189	1227.60	1254	
Out Impedance				50		Ω
	GPS L1	Output = 50 Ω	>+5.5			dBIC
	GPS L2		>+2			
	GPS L5		>+0			
	GNSS L1		>+5.5			
Element Gain	GNSS L2		>+2			
	GNSS L3		>+1.5			
	Galileo E1		>+4.5			
	Galileo E5		>+0			
	Galileo E6		>+1			
	GPS L1		>+30			
	GPS L2		>+30			
	GPS L5		>+30			
	GNSS L1		>+30			
	GNSS L2		>+30			dB
	GNSS L3		>+30			
	Galileo E1		>+30			
	Galileo E5		>+30			
	Galileo E6		>+30			
Output SWR		Output = 50 Ω			2:1	-
Required DC Input Voltage			3.3		12	VDC
LNA Current		Output = 50 Ω			50	mA
LNA OP1dB Compression				10		dBm
LNA OIP3				15		dBm
Noise Figure					3.0	dB
Polarization		Right Hand Circular				
Axial Ratio at Peak		< 2.0 dB Max				
Beam Width		60°±5° at 3 dB				
Altitude		50,000 ft				
Lightning Pro	otection	DC to Ground on the Antenna Element				

# 2 Performance Data2.1.1 L1 Center Frequency

#### Figure 2.1.1. Far Field Plots No Ground Plane





Figure 2.1.1.2. Far Field Plots No Ground Plane



#### **GENERAL DYNAMICS**



#### **MRPA-3SA**

#### **3 Environmental and EMI/EMC Requirements**

## The MRPA-3SA has been designed to meet the following requirements.

Table 3-1. MIL-STD-810 & 461F Requirements

Environment	MIL-STD-Requirements		
Mechanical Vibration	810G	Mtd 514.6, Proc. I	
Functional Shock	810G	Mtd 516.6, Proc. I	
Crash Hazard Shock	810G	Mtd 516.6, Proc. V	
High Temperature	810G	Mtd 501.5, Proc. I & II	
Low Temperature	810G	Mtd 502.5, Proc. I & II	
Temperature Shock	810G	Mtd 503.5, Proc. I-C	
Altitude	810G	Mtd. 500.5, Proc. II & III	
Humidity	810G	Mtd 507.5, Proc. II	
Salt Fog	810G	Mtd 509.5	
Fungus	810G	Mtd 508.6	
Sand and Dust	810G	Mtd 510.5, Proc. I & II	
Conducted Emissions	461F	CE106	
Radiated Emissions	461F	RE102	
Radiated Susceptibility	461F	RS103	


#### **4 Product Options**

Table 4-1. MRPA-3SA Available Options

Туре	Options		
Connector	SMA	Female	
Mount	Side		
	Magnet		
	White	Gloss	
Color (Fed-STD-595)	Black	Matte	
	Green (Standard)	Matte	
	Desert Sand	Matte	
	Gray	Semi-gloss	
Antenna Mounting Plate	AP-3A-RA2		



MRPA-3SA-MM-SF



Note: To have product/part codes customized to meet exact needs, contact GPS Source at GPSS-Sales@gd-ms.com or visit the website at www.gpssource.com

#### **GENERAL DYNAMICS**


Mission Systems



### **MRPA-3SA**

#### **6 Mechanical Drawing**

#### MRPA-3A GPS, Galileo, GLONASS Active Antenna, Side Mount



#### **GENERAL DYNAMICS**

Mission Systems

GPSS-Sales@gd-ms.com • www.gpssource.com Phone: (+1) (719) 421-7300