

SMS COMMAND—VT02S

❖ Setting Part

| COMMAND | DETAILS | DESCRIPTION |
|--|------------------------------|---|
| APN,cmnet# | Set APN | / |
| SERVER,1,vt.protrack365.com/ip,8842# | Set Server | / |
| TIMER,10# | Set GPS data upload interval | Range=3~999s; GPS Uploading interval when ACC ON :default: 10 |
| GMT,E,3,30# | Set time zone | Default: GMT + 8 |
| MODE,1,1200# MODE,1,1200,1300,1400# | Set anti-jammer mode | 1 means MODE=1 1200 = 12:00 , 1300 = 13:00 , 1400 = 14:00 Device will wake up and upload data in 12:00, 13:00, 14:00 every day. |
| MODE,2,10# | Set normal working mode | 2 means MODE=2 ; 10 means GPS data interval is 10 seconds. |

❖ Checking Part

| COMMAND | DETAILS | REPLY |
|----------|----------------------------|--|
| VERSION# | Check firmware version | MTRACK VERSION:VT02S_0780_0003_136_13 |
| PARAM# | Check parameters | SN:355139089215765;APN:CMNET;IP:vt.protrack365.com:8842; CENTER:0;TIMER:10;TimeZone:8.0;LANG:EN;LCWL:OFF;Mode:2; Protocol:ACY;AutoSleep:ENABLE |
| STATUS# | Check GPRS/GPS status | EXT-POWER:12.14V;BATTERY:84%;GPRS;FAIL;GSM Signal:H;GPS:FIXED;GPS Signal:L;ACC:off;PowerMode:Normal; |
| WHERE# | Check location coordinates | Latitude:N22.577156,Longitude:E113.916748,Course:0,Speed:0.34Km/h, Date:2017-03-15,Time:11:33:37, |
| URL# | Check location Google link | (355139089215765)<LocalTime:2017-03-15 11:40:04>http://maps.google.com/maps?q=22.58601,113.85436 |
| RESET# | Restart device | User Request: System Reboot OK. |
| FACTORY# | Factory reset | OK, The terminal will restart after 20 seconds! |