


**USER MANUAL
MULTI LANGUAGE**




Item 71051 Version 1.0
Visit www.trustsmarthome.com
for the latest instructions

SPLASH PROOF JUNCTION BOX


1




2




3




4




5




6




7




8



9



10



1. Open junction box

Loosen the 4 screws on each corner with a screwdriver and remove the cover plate. The screws are fixed to the cover, so they cannot fall out.

2. Position and secure cable glands

Position and secure the cable glands in the position where the wires will be threaded through.

3. Switch off mains power

Switch off the mains power (electric meter box) before installing a receiver

4. Connect wires

Connect the wiring as described in the receiver's installation manual. If applicable, connect the earth wires to the terminal block in the corner of the junction box.

5. Position and secure receiver

The receiver can be positioned in 8 different ways, depending on the wiring. Once in position, secure the the receiver with screws.

6. Tighten cable glands

Tighten the cable glands by turning clockwise to protect the inside from dust and moist. Use 7-12 mm diameter cables for an optimal seal. Other cable sizes can negatively affect the waterproofness of the junction box.

7. Mount junction box

Affix the junction box onto a wall or another surface for extra stability.

8. Switch on mains power

Switch on the mains power (electric meter box) to continue the installation
Shock hazard! Do not contact any exposed wiring. Only touch the plastic housing of this product.

9. Assign transmitter

Read the receiver's manual for the code learning procedure.

10. Close junction box

Put the cover plate back on to the box and tighten the 4 screws on each corner with a screwdriver.

CE Declaration of Conformity

Trust International B.V. declares that this TRUST SMART Home-product:

| | |
|---------------|---------------------------------|
| Model: | OWH-001 WATERPROOF JUNCTION BOX |
| Item number: | 71051 |
| Intended use: | Indoor / outdoor |

is in compliance with the essential requirements and other relevant provisions of the following directives: EMC Directive, Low Voltage Directive and R&TTE Directive.
The product is compatible with the following norms/standards:

EN 60529 (1991+A1:2000)

Legal information

CE: Trust declares this device complies with the Directives as listed in Section 2 of this document.
WEEE: Dispose of the device at a recycling centre. More information: www.trustsmarthome.com
Warranty information: www.trustsmarthome.com/warranty

Authorized representative



H. Donker, Procurement Director
Dordrecht, 1-1-2015

EUROTEC People • Technology • Solutions
HVAC • Refrigeration • Electrical • Measurement

TRUST SMART Home
LAAN VAN BARCELONA 600
3317DD DORDRECHT
NEDERLAND
www.trustsmarthome.com