

StompLight Lithium Ion Power Bank

Power ON and OFF
ON: Push switch to "I" position
OFF: Push switch to "O" position

Capacity Display (aka Fuel Gauge): There are four power indicator LEDs.
Turn on the Power Bank and the stored power capacity will be displayed.
If the Power Bank is turned ON and no indicator LEDs illuminate the Power Bank needs to be recharged.

Capacity light	1 light on	2 light on	3 light on	4 light on
Capacity	25%	50%	75%	100%

Charging the Power Bank:

1. A complete charge takes approximately 6 hours
2. Connect the provided AC-DC charger to power socket (100-240V available)
3. Set the Power Bank to OFF
4. Connect the Power Bank to the AC-DC charger
5. Turn the Power Bank to ON
6. Note that on the AC-DC charger there is a LED displayed. Red indicates charging is taking place. When the Power Bank is fully charged the LED will turn Green. Note: The LED may also show green if the Power Bank is turned OFF when plugged in to the AC-DC charger.
7. The LED on the AC-DC charger will change from red to green when Power Bank reaches 95% power capacity.
8. Once the Power Bank is fully charged turn to OFF "O" preventing power consumption by the four power indicator LEDs.
9. Using the provided AC-DC charger you can charge the Power Bank and power a StompLight Professional or StompLight DMX Slave Light using the included Power Splitter Cable

StompLight Lithium Ion Power Bank (specifications)
Size (cm) 2.8x8.5x14.8 Weight 185 grams !2V Capacity 3000 Input 12.6V 3A max
Charge Time 6 hours Operational Temperature (-4 - 140) Fahrenheit

- Included with Power Bank**
1. DC Power Splitter Cable 5.5x2.1mm-1 Female to 2 Male
 2. AC-DC charger 12.6V = 500mA 100-240V 130mA

- Precautions**
- Protect your Power Bank from exposure, impact, water and rain.
 - Store your Power Bank fully charged. Do not store your Power Bank for long periods of time in a low voltage state. In order to extend service life fully charge your Power Bank every three months.
 - Power Bank should be stored in a cool dry indoor location.
 - Do not short or reverse the circuit of your Power Bank
 - Do not open, disassemble or alter your Power Bank
 - Do not dispose of a Power Bank in fire or water
 - A Power Bank may explode if damaged or disposed in fire
 - If your Power Bank is damaged and internal liquid gets into your eyes, do not rub your eyes, immediately rinse with water and consult a physician.

Contact Us
For any inquires, issues or comments concerning the StompLight Power Bank contact us at info@stomplight.com
You can find answers to Frequently Asked Questions at www.StompLight.com

