

# 4K ULTRA HD SMART NETWORK VIDEO RECORDER WITH FUSION<sup>TM</sup>



## 4K Quality with Extensive Storage and Lorex Fusion Compatibility

Record and view impressive 4K video resolution with a heightened level of detail and definition. As part of the Lorex Fusion™ collection you can tailor your security system to your needs, by pairing with both wired and Wi-Fi cameras of your choice, such as video doorbells, floodlights and sensors. Only receive the most important alerts, thanks to Smart Motion Detection, which can differentiate motion generated from either a person or a vehicle and not for things like weather or swaying branches.

Be confident that your security footage is private and secure with the built-in security grade hard drive - with no hidden monthly fees. Expand your storage, using the dual hard drive bays. With 4K resolution, Fusion™ capabilities, smart home compatibility, expandable storage, and support for Smart Motion Detection – this NVR is designed for your security needs.

## **Features**



4K (8MP) Capable



Supports Person and Vehicle Detection



Supports Active Deterrence



No Hidden Cloud Fees



Smart Home/Voice Control Compatible



Fusion™ Capabilities

N862 Fusion Series lorex.com



## 4K ULTRA HD SMART NETWORK VIDEO RECORDER WITH FUSION $^{TM}$

#### **Picture Perfect**

See more and know more with superior definition and

- Record and view video in up to 4K (8MP) Ultra HD Resolution on all cameras
- View live footage in up to 15fps and digitally zoom in on distant objects for better clarity<sup>2</sup>

## Expand your system with Lorex Fusion™

Tailor your security system to your needs

- Expand your system with up to two Lorex Fusion™ compatible Wi-Fi products such as Wi-Fi cameras, Doorbells, Floodlights, and more³
- Stream and record continuous video from your Wi-Fi cameras on your recorder with Lorex Fusion™
- Increase the limited Wi-Fi SD-Card storage capacity of pair cameras by taking advantage of recording directly to the NVRs built-in HDD

## **Smart Person and Vehicle Detection**

Always know when a person or vehicle is on your property

- Reduce unnecessary alerts and false alarms with Smart motion detection<sup>5</sup>
- Get push notifications when motion from a person or vehicle is detected<sup>7</sup>
- Use Smart Search to filter motion events for reviewing footage quickly and easily

## Local Storage - No Monthly Fees

Keep your footage private and secure

- 2 bay hard drive with up to 2 × 8TB of storage space with no hidden monthly fees
- Local built-in security-grade hard drive
- Heavy-duty hard drive designed for advanced processing and the workload of 24/7 monitoring

#### Home is where the smart is

Enjoy the convenience and control of smart home compatibility and voice control features\*

- Quickly access your live footage with simple voice commands (compatible with Amazon Alexa and Google Assistant)<sup>4</sup>
- View live or recorded video directly on your TV with smart home compatibility (Compatible with: Apple TV and Chromecast)
- \* Not compatible with PAL version.



N862 Fusion Series lorex.com



## **4K ULTRA HD SMART NETWORK VIDEO RECORDER** WITH FUSION™

## **Product Specifications**

General

Video Transmission

Technology

Channels 16 Channels

ΙP

Inputs/Outputs

16 x PoE Video Input

Video Outputs<sup>7</sup> 1 × VGA/1 × HDMI

Audio Input 1 ch: RCA type Audio Output 1 ch: RCA type

Alarm IN 4 channels Alarm OUT 2 channels

Display

Display Output Resolution Up to 4K UHD, Auto Detect

Live Display 1,4,8,9,16

Live Display Speed (Max) up to 4ch 4K@15fps

On/Off System Navigation **USB** Mouse

Recording

Recording Resolution 4K (8MP)/5MP/3MP/ 1080p/720p

Recording Frame Rate 4K@15fps; 5MP@30fps;

1080p@30fps;720p@30fps

Recording Schedule Schedule recordings through Continuous, Motion, Smart

> Motion (Person and Vehicle), Face Detection, Alarm, Day, Hour per

channel

Back-up File Format DAV/ASF/AVI/MP4

Video Compression H.265/H.264

Playback

Simultaneous Playback Up to 4ch@4K15fps

Playback Speed Variable Max 8×

Search By Time/Date, All Motion Events or

Smart Motion (Person/Vehicle<sup>5</sup>),

Area Search

Storage

Hard Drive Bays 2 Bays

Hard Drive Capacity Up to 2 x 8TB (SATA)

Backup Media USB Flash Drive & USB HDD **Special Features** 

**Smart Motion Detection** Yes: Person & Vehicle Motion

Detection<sup>5</sup>

Face Detection Support Yes 6

Active Deterrence Support Yes 6

Panic Button Yes 6

Smart Search Yes

Wired/Wireless Fusion™

supported

Sensor Fusion™

support

Yes

Yes<sup>3</sup>

Smart Home<sup>4</sup>

Voice Control Amazon Alexa™, Google Assistant™

Streaming Options Chromecast™, Apple TV™, Amazon

Echo Show™, Google Home Hub™,

Lenovo Smart Display™

Connectivity

Mobile Viewing Android, iOS

Compatible APP Lorex Home™

PC/Mac Remote Viewing Yes/Lorex Cloud™

**Email Notification** Text and Snapshot

Network Interface 1000 Base-TX, RJ45

Network Bit Rate 200 Mbps total

**DDNS** Yes (Optional)

**USB** interface USB 2.0 × 2

**Additional Specifications** 

FW Upgrade USB/Network

Watchdog Function Yes

**Power Consumption** Approx. 13.2W (no HDD included)

Supply Voltage

Total PoE Power Output PoE: Max 25.5W for single port,

130W total9

100VAC-240VAC, 50/60hz, DC48V/2A

**Unit Dimensions** 14.7 x 12.9 x 2.1" / 375 x 327 x 53 mm  $(W \times D \times H)$ 

Unit Weight 5.8 lbs / 2.6 kg (excl. HDD)

Operating Temperature 14° ~ 131°F / -10° ~ 55°C

Humidity 10 ~ 90% RH

**N862 Fusion Series** lorex.com



## 4K ULTRA HD SMART NETWORK VIDEO RECORDER WITH FUSION™

## Model Information

N862A63B 16-channel 4K NVR with 6-95529-02901-6

3TB HDD

N862A64B 16-channel 4K NVR with 6-95529-02900-9

4TB HDD

### **Dimensions**

Package Plain Box

Package Weight 11.02lb / 4.9kg

Package Dimensions 21.1 × 16.3 × 6.7" /  $(W \times D \times H)$ 538 × 414 × 170mm

Package Cube 0.06cbf / 0.001cbm

## **Back Panel**







## What's in the box







1 × Ethernet cable



1 × Power Adapter



1 × HDMI Cable



1 × USB Mouse



Quick Setup Guide

- 1. 4K (8MP) IP cameras are required to take advantage of 4K recording.
- 2. Recording time may vary based on recording resolution and quality, lighting conditions and movement in the scene.
  3. Fusion™ capabilities are limited to 2 wireless devices per system. Wireless devices require an available channel on the NVR as well as a sufficient signal strength between the device(s) and your Wi-Fi router for video streaming. For full details on Wi-Fi cameras compatibility and instructions, visit <a href="https://www.lorex.com/pages/fusion">www.lorex.com/pages/fusion</a>
- 4. Controlling certain features in your security system requires a compatible smart device. Availability and performance of certain features and services are smart device dependent and may not be available in all areas or networks. For compatibility, features, and instructions visit www.lorex.com/smarthome
- 5. Accuracy of Smart Motion Detection will be influenced by multiple factors, such as the object's distance from the camera, the size of the object, and the height and angle of the camera. Night vision will also impact the accuracy of detection. Compatible with certain Lorex IP cameras only.
- 6. Compatible with certain Lorex IP and select wireless cameras only. For a list of compatible cameras please visit www.lorex.com/compatibility
- 7. Accessing your security system remotely requires a high-speed internet connection. Ensure your NVR has a wired connection to a router (not included). A minimum upload speed of 5Mbps is recommended for reasonable video performance. Up to 3 devices may connect to the system at the same time. For the latest list of supported apps and devices, please visit <a href="https://www.lorex.com/compatibility">www.lorex.com/compatibility</a>
- 8. HDMI output supports 4K HD for high definition multi-channel live or recorded video viewing. Image quality and resolution is dependent on the type of camera connected to the NVR, as well as TV/monitor
- 9. NVR has a total PoE power output of 130w. Different IP cameras have different wattage specifications. Please double check your camera specifications for power consumption (Wattage) requirements in order to not exceed the NVRs power output availability of the recorder when adding cameras. To learn more, please visit www.lorex.com/compatibilitydisclaimer 9: NVR has a total PoE power output of 130w. Different IP cameras have different wattage specifications. Please double check your camera specifications for power consumption (Wattage) requirements in order to not exceed the NVRs power output availability of the recorder when adding cameras. To learn more please visit www.lorex.com/compatibility