

SANGEAN

Rechargeable*

A World of Listening

PR-D7



FM-Stereo / AM / PLL Tuning Portable Receiver

- PLL Synthesized tuning system.
- Available in black or white.
- 10 memory presets (5 FM, 5AM).
- Automatic station search.
- Ultra compact, good for travelling.
- Plays on rechargeable* and alkaline batteries.
- Back light LCD.
- Rotary control for volume.
- Clock.
- Charge indicator.
- Alarm by radio or buzzer.
- Sleep and snooze timer.

*This product can use and recharge rechargeable batteries (NiMH) not included. See over page for technical specifications.

CANOHM

3/200 Turner Street,
Port Melbourne Victoria 3207
Telephone 03 9644 7888
Facsimile 03 9646 7366

Email
sales@canohm.com.au
www.sangean.com.au

SANGEAN

Rechargeable*

A World of Listening

	Model	PR-D7	
Tuning	Type	PLL synthesizer	
	Memory Presets	10	
Display	Type	LCD	
	Size (mm)	81 x 21	
	Back Light	Yes	
Band	FM	Frequency MHz	87.5 - 108, 2, 3
	AM	Frequency kHz	522 - 1629
Clock	Real Time	Yes	
	Alarm Radio	Yes	
	Alarm Buzzer	HWS	
	Snooze	Yes	
	Sleep	Yes	
Output	Speaker Unit	2.5 inch 8 Ohm	
Output Power	AC/DC IN (Speaker)	1.6 W (DC IN)	
	Batteries (Speaker)	600 mW (Ni-HM 7.2V)	
	Earphones	5+5 mW	
Power Supply	DC IN	12V DC 500 mA	
	Batteries (Main power)	6 x 1.5V (UM-3)	
Charge . BT	Charge BT	6 x 1.2V (UM-3)	
I/O Socket	DC in	Yes	
	Earphones	Yes	
Accessories	AC Adaptor	Yes	
Dimensions	W x H x D (mm)	215 x 116 x 40	
	Weight (g)	574	
Warranty		12 months	

PR-D7



E&OE

CANOHM

3/200 Turner Street,
Port Melbourne Victoria 3207
Telephone 03 9644 7888
Facsimile 03 9646 7366

Email
sales@canohm.com.au
www.sangean.com.au