

SANGEAN

A World of Listening

RCR-9



AM / FM Clock Radio

- AM / FM-stereo digital tuning
- 18 station presets (9 FM, 9 AM)
- Easy to read LCD display with adjustable backlight
- Radio controlled clock available for FM RDS-CT
- Time zone selector
- Adjustable tuning step
- 2 alarm timer by radio or buzzer
- HWS (Humane Wake System) buzzer and radio
- Adjustable nap timer
- Adjustable sleep timer
- Snooze function
- 2.5-inch full range speaker
- I/O jacks: Aux-in and headphone

See over page for technical specifications.

CANOHM

3/200 Turner Street,
Port Melbourne Victoria 3207

Telephone 03 9644 7888
Facsimile 03 9646 7366

Email
sales@canohm.com.au

www.canohm.com.au
www.sangean.com.au

ABN 57 004 817 949
September 2014

	Model	RCR-9	
Tuning	Type	DSP Tuner	
	Memory Presets	18 (9 FM / 9 AM)	
Display	LCD / VFD	LCD	
	View Area (mm / inch)	78 x 18 / 3.07 x 0.71	
	Graphic / Character Type	Segment	
	Back Light	Yes	
	Dimmer	Yes	
Feature	Stereo	Earphones	
Tuner	FM	Frequency (MHz) RDS / RBDS	87.5 - 108 PS / PTY / RT / CT
	AM	Frequency (kHz) Adjustable Tuning Step	522 - 1710 Yes
Clock	Real Time	RDS	
	Radio Alarm	HWS	
	Buzzer Alarm	HWS	
	Adjustable Alarm Level	Buzzer / Radio Alarm	
	Snooze	Yes	
	Sleep	Yes	
	NAP Timer	Yes	
Audio	EQ	Loudness on / off	Yes
Output Devices	Speaker	Size (mm / inch)	2 1/2 inches
		Impedance	8 ohms
		Magnetically Shield	Yes
Output Power (Typical)	AC / DC in (Speaker)	0.7W	
	Earphones	3+3mW (32ohm)	
Power Supply	DC in	6V 0.4A	
I/O Socket	AC / DC - in	DC	
	Earphones	Yes	
	Aux - in	Yes	
	Ext. Antenna	FM wire	
Dimensions	W x H x D (mm)	140.6 x 142.6 x 88.2	
	Weight (g)	560	
Warranty		12 months	

RCR-9

