

RA-4961-PRQ

Wireless Indoor PIR Sensor

Features:

- For use with the RA-4961 series receivers
- Wirelessly monitor entryways, rooms, or other areas
- Up to 1,000ft (305m) transmission range*
- Sensing range up to 26ft (8m)
- Programmable activation time
- Runs on batteries for a convenient, wireless installation
- Adjustable mounting angle



RA-4961-PRQ

Specifications:

Model Number		RA-4961-PRQ
Frequency		914.8MHz
Transmission range*		Up to 1,000ft (305m)
Channels		1
Power supply		1x 9VDC Battery (Not Included)
Current Draw	Standby	7µA
	Max	18mA
Estimated battery life		300 days (3 triggers/day)
Low battery indicator		Zone LED on receiver blinks continuously
PIR sensor range		26' (8m)
PIR sensor detection angle		80° horizontal
Operating Temperature		-4°~140°F (-20°~60°C)
Dimensions		2 ⁷ / ₁₆ "x1 ¹⁵ / ₁₆ "x3 ⁹ / ₁₆ " (62x49x90mm)

*Line of sight. Transmission range will vary depending on installation and operating environment.

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606

Phone: (949) 261-2999 | (800) 662-0800 Fax: (949) 261-7326

Website: www.seco-larm.com Email: sales@seco-larm.com



Copyright 2015 © SECO-LARM U.S.A., Inc. All rights reserved.
All trademarks are the property of SECO-LARM U.S.A., Inc. or their respective owners.
The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.

SECO-LARM® ENFORCER® CRIMEBUSTER® CBA SLI®

PI_RA-4961-PRQ_1511210.docx