

New TECHNI-PRINT® 4.0 Heat Transfer Paper

FOR LASER COPIERS OR PRINTERS

TECHNI-PRINT[®] **4.0** Papers are designed for both fuser oil and oil-less laser printers and copiers. They are for the heat transfer of photos and images to light colored T-shirts, sweatshirts, mouse pads, coasters, puzzles, handbags, binders, pad folios, paper, leather, magnets, wood veneer, nylon and more. Choose garments that have a tight weave. This is particularly important when transferring to sweatshirts.

PRINTING:

- 1. Mirror the image.
- 2. Load the paper so that the image will appear on the coated side of the paper.
- **3.** TECHNI-PRINT[®] 4.0 Paper should be fed into the copier or printer with the short dimension first (grain long).
- **4.** Start with "Plain Paper" mode. If toner does not fuse completely, adjust to a heavier paper setting.
- **5.** Trim away the unprinted areas of the transfer if desired.

TRANSFERRING:

Commercial Heat Press Only (No Hand Iron)

- 1. Place the transfer sheet face down on the substrate and press: 30 seconds at 375°F using heavy pressure
- 2. Peel while still hot.

For Use With:









HEAT PRESS TEMPERATURE PRESSURE TIME

375° Heavy 30 Sec.

Laser Printer/Copier

Heat Press

NO Hand Iron

White or Light Color

WASHING INSTRUCTIONS:

Turn garment inside out and wash in cold water using a mild detergent. Do not use bleach. Dry on low heat setting. Do not iron directly on the transferred area.

STORAGE AND HANDLING OF TECHNI-PRINT® 4.0 HEAT TRANSFER PAPERS

Store TECHNI-PRINT[®] 4.0 Papers in a cool, dry area and do not remove from carton or poly bag until you are ready to use.

IMPORTANT

We thoroughly test each of our products on various substrates using different transfer equipment. However, it is impossible for us to duplicate all variables using all substrates and transfer equipment. Therefore, it is essential that you test the paper prior to production using your equipment, methods, and substrate material. Heat presses vary in accuracy. Conduct tests to determine the best time and temperature to use with your equipment. Please keep in mind that the Seller's and Manufacturer's maximum obligation shall be to replace any paper that has proven to be defective. Neither the Seller nor the Manufacturer shall be liable for any injury, direct or consequential, arising out of the use of, or inability to use this paper.

Revised 01/2009



