

# RECOMMENDED CLEANERS FOR EACH MOBIUS PART:

It is recommended that warm or hot water is used to make up your diluted cleaning solution for the Mobius.

MOBIUS PART	RECOMMENDED PH RANGE OF CLEANER	RECOMMENDED CLEANER(S)	RECOMMENDED CLEANING PROCEDURE
BLADE SYSTEM (Helical Blades, Bed Knives, Spacer Bars)	8.5 – 10	<b>STEP 1 - CLEAN</b> - <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or - <a href="#">RESIN8 XTRA</a>  <b>STEP 2 - RINSE</b> with water  <b>STEP 3 - SANITIZE, IF NECESSARY</b> - <a href="#">Shyield</a> or Isopropyl	<b>BED KNIVES &amp; SPACER BARS:</b>  With parts on racks, soak in diluted cleaning solution for 5 – 10 minutes, brush/wipe down any areas with significant resin build-up then rinse. Pressure washer OK.  <b>HELICAL BLADES:</b>  Place helical blades in blade racks. If resin build-up is minimal, simply wipe down with cleaning wipe or cloth. If resin build-up is more significant, spray blades with cleaner, avoiding the bearings on either end, and let sit for 5 minutes. Brush/wipe down any areas with significant resin build-up then rinse. Pressure washer OK on blades, but not on bearing blocks.  To clean bearing blocks, place blades on support racks. Use a cleaning wipe to hand-clean bearing blocks, as necessary
SEPARATOR HOUSING FAN HOUSING (Stainless Steel Versions)	10 - 13	<b>STEP 1 - CLEAN</b> - <a href="#">Super Clean</a> , - <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or - <a href="#">RESIN8 XTRA</a>  <b>STEP 2 - RINSE</b> with water  <b>STEP 3 - SANITIZE, IF NECESSARY</b> - <a href="#">Shyield</a> or Isopropyl	Spray with diluted cleaning solution, let sit for 5 – 10 minutes, brush/wipe down any areas with significant resin build-up then rinse. Pressure washer OK.

MOBIUS PART	RECOMMENDED PH RANGE OF CLEANER	RECOMMENDED CLEANER(S)	RECOMMENDED CLEANING PROCEDURE
SEPARATOR HOUSING FAN HOUSING (Anodized Aluminum Versions)	8.5 – 10	<p><b>STEP 1 - CLEAN</b> - <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or - <a href="#">RESIN8 XTRA</a></p> <p><b>STEP 2 - RINSE</b> with water</p> <p><b>STEP 3 - SANITIZE, IF NECESSARY</b> - <a href="#">Shyield</a> or Isopropyl</p>	Spray with diluted cleaning solution, let sit for 5 – 10 minutes, brush/wipe down any areas with significant resin build-up then rinse. Pressure washer OK.
LID SCREENS BLUE TUMBLER RETAINING RINGS	8.5 – 10	<p><b>STEP 1 - CLEAN</b> - <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or - <a href="#">RESIN8 XTRA</a></p> <p><b>STEP 2 - RINSE</b> with water</p> <p><b>STEP 3 - SANITIZE, IF NECESSARY</b> - <a href="#">Shyield</a> or Isopropyl</p>	Spray with diluted cleaning solution, let sit for 5 – 15 minutes, brush/wipe down areas with significant resin build-up then rinse. Pressure washer OK.
MOBIUS BODY & LID	8.5 – 10	<p><b>STEP 1 - CLEAN</b> - <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or - <a href="#">RESIN8 XTRA</a></p> <p><b>STEP 2 - RINSE</b> with water</p> <p><b>STEP 3 - SANITIZE, IF NECESSARY</b> - <a href="#">Shyield</a> or Isopropyl</p>	<p>Spray areas that require cleaning with diluted cleaning solution. Allow cleaner to sit for 5 – 10 minutes, then wipe down with a cleaning wipe or soft cloth. For areas with significant resin buildup, a plastic razor blade can be used to scrape off resin before wiping down.</p> <p><b>Note 1: Do not pressure wash Mobius body and avoid spraying control panel and other electrical components.</b></p> <p><b>Note 2: Use compressed air to blow down gears and belts on left side of machine.</b></p>

MOBIUS PART	RECOMMENDED PH RANGE OF CLEANER	RECOMMENDED CLEANER(S)	RECOMMENDED CLEANING PROCEDURE
TUMBLER BRUSH	10 – 13	<p><b>STEP 1 - CLEAN</b></p> <ul style="list-style-type: none"> <li>- <a href="#">Super Clean</a>,</li> <li>- <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or</li> <li>- <a href="#">RESIN8 XTRA</a></li> </ul> <p><b>STEP 2 - RINSE</b> with water</p> <p><b>STEP 3 - SANITIZE, IF NECESSARY</b></p> <ul style="list-style-type: none"> <li>- <a href="#">Shyield</a> or Isopropyl</li> </ul>	<p>AUTOMATIC TUMBLER AND BRUSH WASHER: Add 1 part cleaner to 4 parts hot water, turn on, allow tumbler and brush to rotate for 5-10mins. Rinse with water. Apply sanitizer.</p> <p>MANUAL CLEANING: Soak in diluted cleaning solution for 5 – 15 minutes, brush/wipe down any areas with significant resin build-up then rinse. Pressure washer OK.</p>
TRIM TOTE TRIM TOTE GASKET	10 – 13	<p><b>STEP 1 - CLEAN</b></p> <ul style="list-style-type: none"> <li>- <a href="#">Super Clean</a>,</li> <li>- <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or</li> <li>- <a href="#">RESIN8 XTRA</a></li> </ul> <p><b>STEP 2 - RINSE</b> with water</p> <p><b>STEP 3 - SANITIZE, IF NECESSARY</b></p> <ul style="list-style-type: none"> <li>- <a href="#">Shyield</a> or Isopropyl</li> </ul>	<p>Spray with or soak in diluted cleaning solution for 5 – 15 minutes, brush/wipe down any areas with significant resin build-up then rinse. Pressure washer OK.</p>
IMPELLER FAN	10 – 13	<p><b>STEP 1 - CLEAN</b></p> <ul style="list-style-type: none"> <li>- <a href="#">Super Clean</a>,</li> <li>- <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or</li> <li>- <a href="#">RESIN8 XTRA</a></li> </ul> <p><b>STEP 2 - RINSE</b> with water</p> <p><b>STEP 3 - SANITIZE, IF NECESSARY</b></p> <ul style="list-style-type: none"> <li>- <a href="#">Shyield</a> or Isopropyl</li> </ul>	<p>Wipe down impeller blades with a cleaning wipe or cloth, then rinse.</p>

MOBIUS PART	RECOMMENDED PH RANGE OF CLEANER	RECOMMENDED CLEANER(S)	RECOMMENDED CLEANING PROCEDURE
FAN HOUSING FILTER BAG (200 mesh)	10 – 13	<b>STEP 1 - CLEAN</b> - <a href="#">Super Clean</a> , - <a href="#">Tub O' Towels</a> Heavy Duty Cleaning Wipes and/or - <a href="#">RESIN8 XTRA</a>  <b>STEP 2 - RINSE</b> with water  <b>STEP 3 - SANITIZE, IF NECESSARY</b> - <a href="#">Shyield</a> or Isopropyl	Soak in diluted cleaning solution for 5 – 15 minutes, then rinse. Pressure washer OK.
FAN HOUSING FILTER BAG (MERV 8 Material)	N/A	Compressed Air	In a well-ventilated area, use compressed air to blow out the filter bag. Note, filter bag should be replaced on a regular basis.