

INSPECTION

Inspect the equipment according to your department's policy for inspecting life safety equipment. The equipment should be inspected after each use and at least once a year by an inspector that meets your department's training standard for inspection of life safety equipment. Record the date of the inspection and the results in the equipment log or on a tag that attaches to the equipment. Each user should be trained in equipment inspection and should do a cursory inspection and check component compatibility before each use.

When inspecting the equipment, check the cord for cuts, worn or frayed areas, broken fibers, soft or hard spots, discoloration, or melted fibers. Check the knots to ensure they are securely tied. If any of the above are noted, or if the equipment has been subjected to shock loads, fall loads, or abuse other than normal use, remove the equipment from service and destroy it. If there is any doubt about the serviceability of the equipment, remove the it from service and destroy it.

USE

The Helo Tagline is set up by connecting the tagline to the Weak Link using the steel Quick Link. The Quick Link adds weight to the end of the tagline so it will fall if the Weak Link breaks. Connect the tagline to the litter using a carabiner through the Weak Link and around the railing at the foot of the litter. The expected breaking strength of the weak link is 150 - 175 lbf.

CARRYING, MAINTENANCE & STORAGE

During use, carrying, and storage keep the Utility Loop away from acids, alkalis, exhaust emissions, rust and strong chemicals. Do not expose the loop to flame or high temperatures. Carry the Utility Loop where it will be protected as the loop could melt or burn and fail if exposed to flame or high temperatures.

If the Utility Loop becomes soiled, it can be washed in cold water with a mild detergent. CMC Rescue recommends the use of LifeLine Cleaner. Dry out of direct sunlight. Do not dry in an automatic dryer. Store in a cool, dry location.

REPAIR

All repair work shall be performed by the manufacturer. All other work or modifications performed elsewhere may void the warranty, and releases CMC Rescue, Inc. from all liability and responsibility as the manufacturer.

IMPORTANT INFORMATION - PLEASE READ AND SAVE



Helio Tagline Set

Made in USA
of US and foreign
components

PRODUCT LABEL

WARNING

- **SERIOUS INJURY OR DEATH MAY RESULT FROM THE IMPROPER USE OF THIS EQUIPMENT.**
- **THIS EQUIPMENT HAS BEEN DESIGNED AND MANUFACTURED FOR USE BY EXPERIENCED PROFESSIONALS ONLY.**
- **DO NOT ATTEMPT TO USE THIS EQUIPMENT WITHOUT PROPER TRAINING.**
- **USE, INSPECT, AND REPAIR ONLY IN ACCORDANCE WITH MANUFACTURER'S INSTRUCTIONS.**

CMC Rescue, Inc.

6740 Cortona Drive, Goleta CA 93117

USA

805-562-9120 / 800-235-5741

cmcrescue.com

ISO 9001:2008 Certified

©2015 CMC Rescue, Inc. Control No. 724140.01.061813