



Jayden CEILING LIGHT

INSTALLATION GUIDE



WEARING GLOVES
IS RECOMMENDED

DANGER: ELECTRIC SHOCK RISK. FOR YOUR SAFETY,
TURN OFF ELECTRICAL POWER BEFORE BEGINNING
INSTALLATION AND USE CAUTION WHEN INSTALLING.

+1 888.399.9905

www.vault-light.com | sales@vault-light.com



JAYDEN FLOWER CEILING LIGHT

Steps:

- 1.Shut off the main electrical supply from the main fuse box/circuit breaker.
2. Carefully unpack all fixture parts and hardware and lay them on a soft surface for assembly.
- 3.Gently pull wiring down from junction box and allow to hang.
- 4.Remove the mounting plate(A) from the lamp body (E) by loosening the final (D) .
- 5.Attach the mounting plate (A) to wall or junction box using mounting screws(J), and tighten it with a screwdriver.
6. Pull the electrical cord of "J-box"through the exit hole of the mounting plate(A)
- 7.Connect ground wire from ceiling to ground wire from lamp using wire caps (K).
- 8.Attach house wire to lamp wires as shown. Fasten the pairs together with a wire caps
DO NOT REVERSE THE HOT AND NEUTRAL CONNECTIONS OR SAFETY WILL BE COMPROMISED.
- 9.Attachthe lamp body (E)to the mounting plate (A) using 2 finals (D), and tighten them.
- 10 Insert 1 type B 40W bulb (or/CFL 12W or/LED 10W, not included) into the socket (F).
DO NOT EXCEED SPECIFIED MAX WATTAGE.
- 11.Push the acrylic sheet (G) onto the lamp body (E) and lock it with the ball (H).
12. Restore power to junction box and test fixture.

